

EXHIBIT

U.S. PATENT NO. 5,629,733 TO YOUMAN, ET AL.



US005629733A

United States Patent [19][11] **Patent Number:** 5,629,733

Youman et al.

[45] **Date of Patent:** May 13, 1997

[54] **ELECTRONIC TELEVISION PROGRAM GUIDE SCHEDULE SYSTEM AND METHOD WITH DISPLAY AND SEARCH OF PROGRAM LISTINGS BY TITLE**

[75] Inventors: Roger Youman, Wayne, Pa.; Marney Morris, Palo Alto, Calif.

[73] Assignees: News America Publications, Inc., New York, N.Y.; Telecommunications of Colorado, Inc., Englewood, Colo.

[21] Appl. No.: 346,603

[22] Filed: Nov. 29, 1994

[51] Int. Cl.⁵ H04N 7/173

[52] U.S. Cl. 348/7; 348/13; 455/4.2; 345/146; 345/902; 395/327

[58] Field of Search 348/6, 7, 12, 13, 348/906; 455/3.1, 4.2, 5.1, 6.1; 395/156; 345/146, 902; H04N 7/16, 7/173

[56] **References Cited****U.S. PATENT DOCUMENTS**

4,862,390	8/1989	Weiner	364/521
4,914,517	4/1990	Duffield	
5,241,671	8/1993	Reed et al.	395/600
5,253,066	10/1993	Vogel	348/906
5,353,121	10/1994	Young	348/563
5,412,720	5/1995	Hoarty	380/15
5,416,508	5/1995	Sakuma et al.	348/3
5,485,197	1/1996	Hoarty	348/12
5,515,497	5/1996	Itri et al.	395/159

OTHER PUBLICATIONS

May 1993. Vito Brugliera, *Digital On-Screen Display—A New Technology for the Consumer Interface*, 18th International Television Symposium, Montreux, Switzerland, 10–15 Jun.

Sep. 1991. Hirasawa Kazuo, *Patent Abstracts of Japan*, vol. 15, No. 480, "Information Reproducing Device."


Primary Examiner—John K. Peng

Assistant Examiner—Chris Grant

Attorney, Agent, or Firm—Well, Gotshal & Manges LLP

[57] **ABSTRACT**

An electronic program schedule system which includes a receiver for receiving broadcast, satellite or cablecast television programs for a plurality of television channels and a tuner for tuning a television receiver to a selected one of the plurality of channels. A data processor receives and stores in a memory television program schedule information for a plurality of television programs to appear on the plurality of television channels. A user control apparatus, such as a remote controller, is utilized by a viewer to choose user control commands and transmit signals in response to the data processor which receives the signals in response to user control commands. A television receiver is used to display the television programs and television program schedule information. A video display generator receives video control commands from the data processor and program schedule information from the memory and displays a portion of the program schedule information in overlaying relationship with a television program appearing on a television channel in at least one mode of operation of the television programming guide. The data processor controls the video display generator with video control commands, issued in response to the user control commands, to display program schedule information for any chosen one of the plurality of television programs in overlaying relationship with at least one television program then appearing on any chosen one of the plurality of channels on the television receiver.

23 Claims, 57 Drawing Sheets




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 6A




FIG.7




FIG. 8




FIG.9


Premium Services	<input type="button" value="Enter"/>	 5:03pm
▽		
<input type="button" value="HBO"/>	Home Box Office \$10.40/Month	
<input type="button" value="SHO"/>	Showtime \$9.95/Month	
<input type="button" value="DIS"/>	The Disney Channel \$9.95/Month	
<input type="button" value="TMC"/>	The Movie Channel \$1.50/Month	
<input type="button" value="MAX"/>	Cinemax \$9.95/Month	
<input type="button" value="PLA"/>	Playboy at Night \$4.95/Evening(5:00pm to 3:00am)	
<input type="button" value="ACT"/>	Action \$5.95/Day(11:00pm to 3:00pm)	
Movie, special events and family programming!		
You are not a Subscriber. Press <input type="button" value="Enter"/> to Subscribe!		

FIG. 10




FIG. 11




FIG. 12




FIG. 12A




FIG.13




FIG.14




FIG.15




FIG. 16




FIG. 17

All-180 Listings					<div> <div>Enter</div> <div> <div>TV GUIDE</div> <div>7:13 pm</div> </div> </div>	
Baseball (4:30-7:30p)					i	
4 KRON	Today	7:00p	7:30p	8:00p	8:30p	
4 KRON	Baseball	Ent. Tonight	Fresh Prince	Blossom		
5 KPDX	Evening Shade	Major Dad	Murphy Brown			
6 HBO	JFK: In His Own Words	JFK				
7 KGO	Jeopardy!	Wheel of Fortune	Day One			

FIG. 18

Listings By

Category *190A 190B* *190D* *190C*

Today

<input type="button" value="22 LIF"/>	4:00p A Case of Deadly Force	<input type="button" value="i"/>
<input type="button" value="1 HOT"/>	4:00p Ring of Fire II: Blood and Steel	<input type="button" value="i"/>
<input type="button" value="34 AMC"/>	4:00p Texas Across the River	<input type="button" value="i"/>
<input type="button" value="31 MAX"/>	4:00p The Ballad of the Sad Cafe	<input type="button" value="i"/>
<input type="button" value="8 SHO"/>	5:00p Big Girls Don't Cry - They Get Even	<input type="button" value="i"/>
<input type="button" value="46 BRV"/>	5:00p Queen of Hearts	<input type="button" value="i"/>
<input type="button" value="27 TMC"/>	5:00p The Roaring Twenties	<input type="button" value="i"/>
<input type="button" value="25 TBS"/>	5 05p No Mercy	<input type="button" value="i"/>

FIG. 19

Listings By ²⁰¹ Channel ^{202a} ^{202b} ^{202c} ^{202d} ^{202e} ^{202f} ^{202g} ^{202h} ²⁰²ⁱ ^{202j} ^{202k} ^{202l} ^{202m} ²⁰²ⁿ ^{202o} ^{202p} ^{202q} ^{202r} ^{202s} ^{202t} ^{202u} ^{202v} ^{202w} ^{202x} ^{202y} ^{202z} ^{202aa} ^{202ab} ^{202ac} ^{202ad} ^{202ae} ^{202af} ^{202ag} ^{202ah} ^{202ai} ^{202aj} ^{202ak} ^{202al} ^{202am} ^{202an} ^{202ao} ^{202ap} ^{202aq} ^{202ar} ^{202as} ^{202at} ^{202au} ^{202av} ^{202aw} ^{202ax} ^{202ay} ^{202az} ^{202ba} ^{202bb} ^{202bc} ^{202bd} ^{202be} ^{202bf} ^{202bg} ^{202bh} ^{202bi} ^{202bj} ^{202bk} ^{202bl} ^{202bm} ^{202bn} ^{202bo} ^{202bp} ^{202bq} ^{202br} ^{202bs} ^{202bt} ^{202bu} ^{202bv} ^{202bw} ^{202bx} ^{202by} ^{202bz} ^{202ca} ^{202cb} ^{202cc} ^{202cd} ^{202ce} ^{202cf} ^{202cg} ^{202ch} ^{202ci} ^{202cj} ^{202ck} ^{202cl} ^{202cm} ^{202cn} ^{202co} ^{202cp} ^{202cq} ^{202cr} ^{202cs} ^{202ct} ^{202cu} ^{202cv} ^{202cw} ^{202cx} ^{202cy} ^{202cz} ^{202da} ^{202db} ^{202dc} ^{202dd} ^{202de} ^{202df} ^{202dg} ^{202dh} ^{202di} ^{202dj} ^{202dk} ^{202dl} ^{202dm} ^{202dn} ^{202do} ^{202dp} ^{202dq} ^{202dr} ^{202ds} ^{202dt} ^{202du} ^{202dv} ^{202dw} ^{202dx} ^{202dy} ^{202dz} ^{202ea} ^{202eb} ^{202ec} ^{202ed} ^{202ee} ^{202ef} ^{202eg} ^{202eh} ^{202ei} ^{202ej} ^{202ek} ^{202el} ^{202em} ^{202en} ^{202eo} ^{202ep} ^{202eq} ^{202er} ^{202es} ^{202et} ^{202eu} ^{202ev} ^{202ew} ^{202ex} ^{202ey} ^{202ez} ^{202fa} ^{202fb} ^{202fc} ^{202fd} ^{202fe} ^{202ff} ^{202fg} ^{202fh} ^{202fi} ^{202fj} ^{202fk} ^{202fl} ^{202fm} ^{202fn} ^{202fo} ^{202fp} ^{202fq} ^{202fr} ^{202fs} ^{202ft} ^{202fu} ^{202fv} ^{202fw} ^{202fx} ^{202fy} ^{202fz} ^{202ga} ^{202gb} ^{202gc} ^{202gd} ^{202ge} ^{202gf} ^{202gg} ^{202gh} ^{202gi} ^{202gj} ^{202gk} ^{202gl} ^{202gm} ^{202gn} ^{202go} ^{202gp} ^{202gq} ^{202gr} ^{202gs} ^{202gt} ^{202gu} ^{202gv} ^{202gw} ^{202gx} ^{202gy} ^{202gz} ^{202ha} ^{202hb} ^{202hc} ^{202hd} ^{202he} ^{202hf} ^{202hg} ^{202hh} ^{202hi} ^{202hj} ^{202hk} ^{202hl} ^{202hm} ^{202hn} ^{202ho} ^{202hp} ^{202hq} ^{202hr} ^{202hs} ^{202ht} ^{202hu} ^{202hv} ^{202hw} ^{202hx} ^{202hy} ^{202hz} ^{202ia} ^{202ib} ^{202ic} ^{202id} ^{202ie} ^{202if} ^{202ig} ^{202ih} ²⁰²ⁱⁱ ^{202ij} ^{202ik} ^{202il} ^{202im} ²⁰²ⁱⁿ ^{202io} ^{202ip} ^{202iq} ^{202ir} ^{202is} ^{202it} ^{202iu} ^{202iv} ^{202iw} ^{202ix} ^{202iy} ^{202iz} ^{202ja} ^{202jb} ^{202jc} ^{202jd} ^{202je} ^{202jf} ^{202jg} ^{202jh} ^{202ji} ^{202jj} ^{202jk} ^{202jl} ^{202jm} ^{202jn} ^{202jo} ^{202jp} ^{202jq} ^{202jr} ^{202js} ^{202jt} ^{202ju} ^{202jv} ^{202jw} ^{202jx} ^{202jy} ^{202jz} ^{202ka} ^{202kb} ^{202kc} ^{202kd} ^{202ke} ^{202kf} ^{202kg} ^{202kh} ^{202ki} ^{202kj} ^{202kk} ^{202kl} ^{202km} ^{202kn} ^{202ko} ^{202kp} ^{202kq} ^{202kr} ^{202ks} ^{202kt} ^{202ku} ^{202kv} ^{202kw} ^{202kx} ^{202ky} ^{202kz} ^{202la} ^{202lb} ^{202lc} ^{202ld} ^{202le} ^{202lf} ^{202lg} ^{202lh} ^{202li} ^{202lj} ^{202lk} ^{202ll} ^{202lm} ^{202ln} ^{202lo} ^{202lp} ^{202lq} ^{202lr} ^{202ls} ^{202lt} ^{202lu} ^{202lv} ^{202lw} ^{202lx} ^{202ly} ^{202lz} ^{202ma} ^{202mb} ^{202mc} ^{202md} ^{202me} ^{202mf} ^{202mg} ^{202mh} ^{202mi} ^{202mj} ^{202mk} ^{202ml} ^{202mm} ^{202mn} ^{202mo} ^{202mp} ^{202mq} ^{202mr} ^{202ms} ^{202mt} ^{202mu} ^{202mv} ^{202mw} ^{202mx} ^{202my} ^{202mz} ^{202na} ^{202nb} ^{202nc} ^{202nd} ^{202ne} ^{202nf} ^{202ng} ^{202nh} ²⁰²ⁿⁱ ^{202nj} ^{202nk} ^{202nl} ^{202nm} ²⁰²ⁿⁿ ^{202no} ^{202np} ^{202nq} ^{202nr} ^{202ns} ^{202nt} ^{202nu} ^{202nv} ^{202nw} ^{202nx} ^{202ny} ^{202nz} ^{202oa} ^{202ob} ^{202oc} ^{202od} ^{202oe} ^{202of} ^{202og} ^{202oh} ^{202oi} ^{202oj} ^{202ok} ^{202ol} ^{202om} ^{202on} ^{202oo} ^{202op} ^{202oq} ^{202or} ^{202os} ^{202ot} ^{202ou} ^{202ov} ^{202ow} ^{202ox} ^{202oy} ^{202oz} ^{202pa} ^{202pb} ^{202pc} ^{202pd} ^{202pe} ^{202pf} ^{202pg} ^{202ph} ^{202pi} ^{202pj} ^{202pk} ^{202pl} ^{202pm} ^{202pn} ^{202po} ^{202pp} ^{202pq} ^{202pr} ^{202ps} ^{202pt} ^{202pu} ^{202pv} ^{202pw} ^{202px} ^{202py} ^{202pz} ^{202qa} ^{202qb} ^{202qc} ^{202qd} ^{202qe} ^{202qf} ^{202qg} ^{202qh} ^{202qi} ^{202qj} ^{202qk} ^{202ql} ^{202qm} ^{202qn} ^{202qo} ^{202qp} ^{202qq} ^{202qr} ^{202qs} ^{202qt} ^{202qu} ^{202qv} ^{202qw} ^{202qx} ^{202qy} ^{202qz} ^{202ra} ^{202rb} ^{202rc} ^{202rd} ^{202re} ^{202rf} ^{202rg} ^{202rh} ^{202ri} ^{202rj} ^{202rk} ^{202rl} ^{202rm} ^{202rn} ^{202ro} ^{202rp} ^{202rq} ^{202rr} ^{202rs} ^{202rt} ^{202ru} ^{202rv} ^{202rw} ^{202rx} ^{202ry} ^{202rz} ^{202sa} ^{202sb} ^{202sc} ^{202sd} ^{202se} ^{202sf} ^{202sg} ^{202sh} ^{202si} ^{202sj} ^{202sk} ^{202sl} ^{202sm} ^{202sn} ^{202so} ^{202sp} ^{202sq} ^{202sr} ^{202ss} ^{202st} ^{202su} ^{202sv} ^{202sw} ^{202sx} ^{202sy} ^{202sz} ^{202ta} ^{202tb} ^{202tc} ^{202td} ^{202te} ^{202tf} ^{202tg} ^{202th} ^{202ti} ^{202tj} ^{202tk} ^{202tl} ^{202tm} ^{202tn} ^{202to} ^{202tp} ^{202tq} ^{202tr} ^{202ts} ^{202tt} ^{202tu} ^{202tv} ^{202tw} ^{202tx} ^{202ty} ^{202tz} ^{202ua} ^{202ub} ^{202uc} ^{202ud} ^{202ue} ^{202uf} ^{202ug} ^{202uh} ^{202ui} ^{202uj} ^{202uk} ^{202ul} ^{202um} ^{202un} ^{202uo} ^{202up} ^{202uq} ^{202ur} ^{202us} ^{202ut} ^{202uu} ^{202uv} ^{202uw} ^{202ux} ^{202uy} ^{202uz} ^{202va} ^{202vb} ^{202vc} ^{202vd} ^{202ve} ^{202vf} ^{202vg} ^{202vh} ^{202vi} ^{202vj} ^{202vk} ^{202vl} ^{202vm} ^{202vn} ^{202vo} ^{202vp} ^{202vq} ^{202vr} ^{202vs} ^{202vt} ^{202vu} ^{202vv} ^{202vw} ^{202vx} ^{202vy} ^{202vz} ^{202wa} ^{202wb} ^{202wc} ^{202wd} ^{202we} ^{202wf} ^{202wg} ^{202wh} ^{202wi} ^{202wj} ^{202wk} ^{202wl} ^{202wm} ^{202wn} ^{202wo} ^{202wp} ^{202wq} ^{202wr} ^{202ws} ^{202wt} ^{202wu} ^{202wv} ^{202ww} ^{202wx} ^{202wy} ^{202wz} ^{202xa} ^{202xb} ^{202xc} ^{202xd} ^{202xe} ^{202xf} ^{202xg} ^{202xh} ^{202xi} ^{202xj} ^{202xk} ^{202xl} ^{202xm} ^{202xn} ^{202xo} ^{202xp} ^{202xq} ^{202xr} ^{202xs} ^{202xt} ^{202xu} ^{202xv} ^{202xw} ^{202xx} ^{202xy} ^{202xz} ^{202ya} ^{202yb} ^{202yc} ^{202yd} ^{202ye} ^{202yf} ^{202yg} ^{202yh} ^{202yi} ^{202yj} ^{202yk} ^{202yl} ^{202ym} ^{202yn} ^{202yo} ^{202yp} ^{202yq} ^{202yr} ^{202ys} ^{202yt} ^{202yu} ^{202yv} ^{202yw} ^{202yx} ^{202yy} ^{202yz} ^{202za} ^{202zb} ^{202zc} ^{202zd} ^{202ze} ^{202zf} ^{202zg} ^{202zh} ^{202zi} ^{202zj} ^{202zk} ^{202zl} ^{202zm} ^{202zn} ^{202zo} ^{202zp} ^{202zq} ^{202zr} ^{202zs} ^{202zt} ^{202zu} ^{202zv} ^{202zw} ^{202zx} ^{202zy} ^{202zz} ^{202aa} ^{202ab} ^{202ac} ^{202ad} ^{202ae} ^{202af} ^{202ag} ^{202ah} ^{202ai} ^{202aj} ^{202ak} ^{202al} ^{202am} ^{202an} ^{202ao} ^{202ap} ^{202aq} ^{202ar} ^{202as} ^{202at} ^{202au} ^{202av} ^{202aw} ^{202ax} ^{202ay} ^{202az} ^{202ba} ^{202bb} ^{202bc} ^{202bd} ^{202be} ^{202bf} ^{202bg} ^{202bh} ^{202bi} ^{202bj} ^{202bk} ^{202bl} ^{202bm} ^{202bn} ^{202bo} ^{202bp} ^{202bq} ^{202br} ^{202bs} ^{202bt} ^{202bu} ^{202bv} ^{202bw} ^{202bx} ^{202by} ^{202bz} ^{202ca} ^{202cb} ^{202cc} ^{202cd} ^{202ce} <




FIG. 21




FIG. 22


Pay Per View	<input type="button" value="Enter"/>					
Ordering	▼	5:49 PM				
Passenger 57		\$ 3.99				
What time would you like this show to start?						
Today 9:00p	230B	230C				
Tomw 12:00p						
Tomw 6:00p						
Would you like to see a countdown onscreen just before the show start						
		Yes No				
<table border="1"><tr><td>PPV</td><td>/</td></tr><tr><td>/</td><td>Source</td></tr></table>		PPV	/	/	Source	
PPV	/					
/	Source					

FIG.23


Pay Per View Confirmation	◀	Enter	 5:49pm						
You have requested to order:									
Passenger 57		\$ 3.99							
NO, I DO NOT WANT TO ORDER.									
<table border="1"><tr><td>PPV</td><td>/</td><td></td></tr><tr><td>/</td><td>Source</td><td></td></tr></table>				PPV	/		/	Source	
PPV	/								
/	Source								

FIG.24


Pay Per View Confirmation	 Jun 7				
You have requested to order :					
Passenger 57	\$ 3.99				
Yes, I would like to order					
Passenger 57 has been Ordered! Tune to Channel 1 Today at 9:00pm.					
<table border="1"><tr><td>PPV</td><td>/</td></tr><tr><td>/</td><td>Source</td></tr></table>		PPV	/	/	Source
PPV	/				
/	Source				

FIG.24A

LISTINGS		 Listing 		6:06P AUG 16		
5:00	5:30	6:00	6:30	7:00	7:30	8:00
NBC 4 News						
ABC 6 News						
CBS 10 CBS News						
Fox 28 Club Paradise (5:00)						
PBS 29 Mystery!						
COM 30 Tribute to Carson						
HBO 33 Gremlins 2: The New Batch						
ESN 34 Tennis (4:30)						
AMC 35 Arise my Love (5:00)						
DSC 37 Natural World						
NIK 38 I Love Lucy						

FIG.25


Premium Services	<input type="button" value="Enter"/>	 5:03pm
▽		
<input type="button" value="HBO"/>	Home Box Office \$10.40/Month	
<input type="button" value="SHO"/>	Showtime \$9.95/Month	
<input type="button" value="DIS"/>	The Disney Channel \$9.95/Month	
<input type="button" value="TMC"/>	The Movie Channel \$1.50/Month	
<input type="button" value="MAX"/>	Cinemax \$9.95/Month	
<input type="button" value="PLA"/>	Playboy at Night \$4.95/Evening(5:00pm to 3:00am)	
<input type="button" value="ACT"/>	Action \$5.95/Day(11:00pm to 3:00pm)	
Movie, special events, and family programming!		
You are not a Subscriber. Press <input type="button" value="Enter"/> to Subscribe!		

FIG.26




FIG. 27


<p>Cable System Messages</p> <div data-bbox="153 297 273 413"><p>5:52 pm</p></div>	<p>Pay Per View is featuring "Batman Returns" this month.</p> <p>Get a free sneak peek of HBO this weekend.</p>	<p>Complete MSO Title</p>
---	---	---------------------------

FIG.28




FIG. 28A

Billing



Name: TV Guide Onscreen A cct. #: 12345-098765-08-9

Billed From: 05/25/93 Billed To: 06/25/93 Total: \$3.99

FOR CUSTOMER SERVICE CALL: 790-0900

Date	Time	Service / PPV Event	Cost
06/07/93	9:00 p	PASSENGER 57	\$3.99

FIG.29




FIG.30




FIG. 31




FIG. 32




FIG. 33

STORIES



US World News**Cubans use Vitamins to combat epidemic**

Geneva - A costly campaign to provide vitamins to all Cubans has helped curb a mysterious epidemic that has afflicted thousands with vision problems, a World Health Organization official said yesterday.

The outbreak of optical neuritis has dimmed the vision of about 20,000 Cubans and a related malady has affected 6,000 other people, mostly women.

FIG.34

SPORTS



Major League Baseball

Yesterday in National League Action

Colorado 7, Houston 5


San Francisco 5, Chicago 4

Yesterday in American League Action

Detroit 4, Boston 1

Toronto 4, Milwaukee 2

FIG.35






FIG. 36B




FIG. 36C





FIG. 36D

201

TV
GUIDE

LOCATOR



Broadcast:	◀	2 KWGN	3 PPV	4 KCNC	◀
Cable:	◀	41 A&E	3 AMC	24 BET	◀
Premium:	◀	21 DIS	18 ENC	14 HBO	◀
PPV:		11 REQ1	15 REQ2		

Clear ALL favorite channels

Favorite Channel

Included

Excluded

Press * — Lines to illustrate text

FIG. 37




FIG.38




FIG. 38A

FIG. 38B




FIG. 38C

TV
GUIDE

TITLE: 7:34

To search index below, press **OK**

	A-List	COM 47 11PM
	A-Team	KCAL 9 Tmrw 2AM
	A.Hitchcock	NIK 48 Tmrw 1AM
	A.Hitchcock	SCIFI 42 Tmrw 4:30PM
	A.Hitchcock	SCIFI 42 Tmrw 8:30PM
	A.M. Weather	KCET 28 Tmrw 5:30 AM
	ABC News	KABC 7 6:30 PM
	ABC News	KABC 7 Tmrw 5:30AM

325

FIG. 38D

TV GUIDE

TITLE: ☐ M ☐ A ☐ D ☐ 22 KWHY ☐

To return above, press ◀ or ▶

330

◀

Mad About You ☒ 335

Made in America

Magic Box

Magic Box

MagicKid

Magic School Bus

Magnum, P.I.

Magnum, P.I.

KNBC 4 8:30PM

MAX 37 9:30AM ☒

TLC 44 Tmrw 4 AM

TLC 44 Tmrw 6:30AM

HBO 23 Tmrw 1 PM ☒

KLCS 58 Tmrw 9:15AM

KTLA 5 10 AM

USA 17 1PM

▶

FIG.38E




FIG. 38F

TV
GUIDE

Movie
Rating: ◀ ☒ PG PG-13 R ▶

Parental
Guidance: ◀ Adult Themes Sexual Situations ▶

Channel: ◀ 2 KWGN 3 PPV ☒ 4 KONC ☐ ▶

Locked
Program: To lock out a program or series. see "Help"

Lockout
Code: Clear Change

FIG. 39

260

TV
GUIDE

275

Text Location:

Lockout Code:

265

Purchase Code:

270

This button sets the text location to the bottom of the
Screen.
Press to select

FIG. 40




FIG. 40A




FIG. 40B




FIG. 40C




FIG. 40D




FIG. 40E




FIG.4I




FIG. 42

ELECTRONIC TELEVISION PROGRAM GUIDE SCHEDULE SYSTEM AND METHOD WITH DISPLAY AND SEARCH OF PROGRAM LISTINGS BY TITLE

BACKGROUND OF THE INVENTION

This invention relates to an electronic program schedule system, which provides a user with schedule information for broadcast or cablecast programs viewed by the user on a television receiver. More particularly, it relates to an improved electronic program guide that provides the user with a more powerful and convenient operating environment, while, at the same time, increasing the efficiency of navigation by the user through the guide.

Electronic program guides for television systems are known in the art. For example, one prior system used an electronic character generator to display textual schedule information on the full screen of a television receiver. Other prior systems presented electronically stored program schedule information to a user for viewing while allowing the user to select display formats. Still other systems employed a data processor to input user-selection criteria, then stored only the program schedule information meeting these criteria, and subsequently used the stored information to automatically tune a programmable tuner or activate a recording device at the time of broadcast of the selected television programs. Such prior systems are generally discussed in "Stay Tuned for Smart TV," published in the November 1990 issue of *Popular Science*.

Collectively, the prior electronic program systems may be difficult to implement and cumbersome to use. They also fail to provide viewing capabilities that address in a more realistic manner the viewing habits of the users of these electronic program systems. Moreover, many of these systems are complex in their design and are expensive to implement. Ease of use and economy are primary concerns of television program distributors and viewers as they contemplate dramatic increases in the number and nature of program networks and other television-based services. And, as the number of television channels available to a user increases dramatically with the advent of new satellite and cable-based technologies, the utility of these prior systems substantially diminishes.

These prior-art systems also fail to provide the user with sufficient information, for example pricing and the like, about pay-per-view events, premium services or other packaged programming to which the user does not subscribe, nor do they provide the user with the capability to automatically purchase such programming on demand or impulse. Moreover, these prior-art systems are deficient in that they fail to provide an efficient and automatic method of updating or replacing the application software programs that implement the electronic guide at the user sites, relying instead on manual or other cumbersome forms of revision or replacement or hardware-based systems that can not be updated without physical replacement of integrated circuits and/or other parts.

Nor do these prior electronic guide systems have the capability of linking the user to other applications or information systems which are not part of the electronic program guide application or data.

Nor do these prior electronic guide systems provide video promotion of television programs and services that are functionally linked and visually displayed in an integrated fashion. Program promotion is an important element of the effective marketing of television programming. The promo-

tion of pay-per-view pay (i.e., "a la carte") programs and other unregulated program services is particularly important to cable television operators in the wake of re-regulation by the federal government. The current method of promoting such programming using video is through dedicated "barker" channels that use full screen continuous trailers (i.e., previews) which may or may not be accompanied by prices and ordering information. Recently, such promotional videos have been shown in split screens where part of the screen shows general schedule information for a time period roughly corresponding to the time period during which the general program being promoted is shown. Accordingly, there exists a need for an electronic program guide which can provide improved display and linking of video promotions with program schedule information and order processing functions.

The prior electronic program guides also fail to provide the user with a simple and efficient method of controlling access to individual channels and individual programs. The amount of adult situations involving sex and violence has steadily increased during the last 40 years. The issue of how this affects children or other viewers has gained national attention. Providing a parent with the ability to lock-out a channel is a well known and widespread feature of certain television receivers and cable converter boxes. Despite this availability, the feature is seldom used by parents. The main impediments to its effective use are the cumbersome ways in which it is generally implemented, as well as the requirement that entire channels be blocked in order to block access to any objectional programming. A channel-oriented parental lock is unfair to other programmers on the blocked channel—who, for example, offer adult-oriented programming in the evening and youth-oriented programming the following morning—and inconvenient for viewers who want access to such programs. Thus, there is a particular need for a system which provides password control to individual programs and channels using a flexible and uncomplicated on-screen user interface.

The prior electronic program guides are also deficient in that they do not provide the user with the ability to view on demand current billing status and, thus, a need exists for a system which can provide the user with current billing information on the user's demand.

An additional problem with prior program guides is that when displaying schedule information in grid format, i.e., columns representing time slots and rows representing channels, program titles generally are width-wise truncated to fit into the cells of the grid. The width of a grid cell varies with the duration of the program. Since a 30 minute program is allotted only a small amount of space for the program title and description, titles and/or descriptions for half and even full hour programs often must be truncated in order to fit into the allotted space. Some systems simply cut off the description of a program without abbreviating it in any way, such that the user is unable to determine the subject matter of the program. For example, a recent television program display included the following text in a grid cell: "Baseball: Yankees v." Although some systems partially alleviate this problem by providing two lines of text in each grid cell, this solution is not ideal because program descriptions may still be truncated.

A similar problem arises as the time slots change, either automatically or in response to a user control command. Typically, 90 minutes of schedule information is displayed at one time and the 90 minute window is shiftable in 30-minute increments. In the case where a 30 minute shift causes a 30 minute size grid cell to display, e.g., a two-hour movie, it is

likely that the full title of the movie will not fit into the cell. Truncation of the title is thus required in this situation as well. In this case, while two lines of text may be desirable to fit the title in the 30 minute cell, the 60 and 90 minute cells may require only one line of text to display the title.

The prior electronic program guides also lack a method for creating a viewing itinerary electronically while still viewing a program currently appearing on the television receiver. Moreover, these prior program guides leave much guess work for the user as he navigates through a sequence of channels. When skimming through channels to ascertain the program then being displayed on any channel, commonly known as "channel surfing," the user needs to guess which program is currently being aired from the video encountered as the user surfs through the channels. Since much—in some cases, up to 30%—of the programming appearing on any given channel at any given time is advertising or other commercial programming, the user is not provided with any clues as to what program is appearing on a selected channel at a given time and must therefore wait until the advertisement or commercial is over before ascertaining the program then appearing on the selected channel. Thus a need exists for a program guide which displays current program schedule information for each channel as the user surfs through the available channels.

Prior art program guides also lack a means for locating a television program where only the title of the program, movie, or event is known.

Accordingly, there is a need in the art for a simplified electronic program schedule system that may be more easily implemented, and which is appealing and efficient in operation. There is also a need to provide the user with an electronic program schedule system that displays both broadcast programs and electronic schedule information in a manner not previously available with other electronic program schedule systems, particularly those using a remote controller.

For example, there is a particular need for a flexible program schedule system that allows a user to view selected broadcast programs on a portion of the screen of the television receiver while simultaneously viewing program schedule information for other channels and/or services on another portion of the screen. There is also a need for such a program schedule system that permits the user to select from a plurality of selectable display formats for viewing the program schedule information. It is also preferred to have a system that indicates to the user those keys on the remote controller that are active in any particular mode of operation. There also exists a need for such a system that will give a user the capability to set a programmable reminder for viewing a program scheduled to air at a future time.

There is also a need for an electronic guide system providing the user with comprehensive information about pay-per-view events, premium services or other packaged programming to which the user does not ordinarily subscribe, and which provides the user with the capability to automatically purchase such programming on demand or impulse. There is also a need for an electronic guide system providing a reliable and efficient method of updating or replacing the application software that implements the electronic guide at the user sites.

There also exists a need for an electronic program guide that operates as a shell or window to provide the user with the capability to access other applications or information systems that are not part of the electronic program guide application or data.

It is accordingly an object of the present invention to provide a system that will allow the user to view a broadcast program while, at the same time, interactively viewing program schedule information for other programs.

It is another object of the present invention to provide the user with the ability to select from among a plurality of display formats for the program schedule information.

It is yet another object of the present invention to indicate to the user of the program schedule system those keys on the remote controller active in the particular mode of operation of the system at the time of use.

It is a still further object of the present invention to provide the user of the electronic program schedule system with the capability of setting programmable reminder messages for any future program.

It is yet a further object of this invention to provide the system user with comprehensive information about pay-per-view events, premium services or other packaged programming to which the user does not subscribe and the capability to automatically purchase such programming on demand or impulse.

It is another object of the present invention to provide an electronic guide system that provides a reliable and efficient method of updating or replacing the application software programs that implement the electronic guide at the user sites.

It is still another object of the electronic program guide to operate as a shell or window to provide the user with the capability to access other applications or information systems which are not part of the electronic program guide application or data.

It is yet another object of the electronic program guide to provide a system whereby video promotion of television programs and services are functionally linked and visually displayed in an integrated fashion to facilitate the marketing and sale of such programs and services.

It is still a further object of the present invention to provide password control for access to individual programs, as well as channels, using a protected interactive flexible and uncomplicated on-screen interface.

Another object of the present invention is to provide the user with current programming information for all programs as the user surfs through the available channels.

It is yet a further object of the present invention to provide a system in which the user can access his current billing information on demand.

It is another object of the present invention to provide a system which overlays television program listings against varying background views.

It is yet another object of the present invention to provide an improved display of text in the grid cells comprising a page of television program listings.

It is another object of the invention to provide a system where the user can locate a television program, movie or event by selecting the first several characters of the title of the program, movie, or event.

These and other objects of the invention are achieved by an electronic program schedule system which includes a receiver for receiving broadcast, satellite or cablecast television programs for a plurality of television channels and a tuner for tuning a television receiver to a selected one of the plurality of channels. A data processor receives and stores in a memory television program schedule information for a plurality of television programs to appear on the plurality of television channels. A user control apparatus, such as a

remote controller, is utilized by a viewer to choose user control commands and transmit signals in response to the data processor or which receives the signals in response to user control commands. A television receiver is used to display the television programs and television program schedule and other information. A video display generator receives video control commands from the data processor and program schedule information from the memory and displays a portion of the program schedule information in overlaying relationship with a television program appearing on a television channel in at least one mode of operation of the television programming guide. The data processor controls the video display generator with video control commands, issued in response to the user control commands, to display program schedule information for any chosen one of the plurality of television programs in overlaying relationship with at least one television program then appearing on any chosen one of the plurality of channels on the television receiver.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing various components of the preferred embodiment of the invention herein.

FIG. 2 is a block diagram showing the combination of program and schedule information by the video overlay device utilized in the preferred embodiment of the invention.

FIG. 3 depicts a remote controller that can be used in connection with the preferred embodiment of the electronic program guide system of the present application.

FIG. 4 depicts an alternative embodiment of the remote controller shown in FIG. 3.

FIG. 5 shows an overlay appearing on a television screen in one mode of operation of the preferred embodiment of the present invention.

FIG. 6 is a menu that appears on a television screen in a MENU mode of operation of the preferred embodiment of the present invention.

FIG. 6A is yet another menu that appears on a television screen in a MENU mode of operation of the preferred embodiment of the present invention.

FIG. 7 depicts a Viewer Preference Menu that appears on a television screen in one aspect of the preferred embodiment of the present invention.

FIG. 8 shows a Preferred Channel selection submenu.

FIG. 9 shows an impulse ordering menu that appears on a television screen in one aspect of the preferred embodiment of the present invention.

FIG. 10 shows a Premium Services submenu that appears in one mode of operation of the preferred embodiment of the present invention.

FIG. 11 shows a graphic overlay appearing on a television screen in a BROWSE mode of operation of the preferred embodiment of the present invention.

FIG. 12 shows a graphic overlay appearing on a television screen in a BROWSE mode of operation of the preferred embodiment of the present invention having different information from that shown in FIG. 11.

FIG. 12A shows a graphic overlay appearing on a television screen in a BROWSE mode of operation in the present invention displaying schedule information for a time and channel other than that shown in FIG. 11.

FIG. 13 shows a graphic overlay appearing in a REMINDER mode of operation of the preferred embodiment of the present invention.

FIG. 14 shows yet another graphic overlay appearing in a REMINDER mode of operation of the preferred embodiment of the present invention.

FIG. 15 is yet another menu that appears on a television screen in a MENU mode of operation of the preferred embodiment of the present invention.

FIG. 16 is yet another menu that appears on a television screen in a MENU mode of operation of the preferred embodiment of the present invention.

FIG. 17 is yet another menu that appears on a television screen in a MENU mode of operation of the preferred embodiment of the present invention.

FIG. 18 shows a grid listing of schedule information displayed in an All Listings mode of operation of the preferred embodiment of the present invention.

FIG. 19 shows schedule information displayed in a Listings By Category mode of operation of the preferred embodiment of the present invention.

FIG. 20 shows schedule information displayed in a Listings By Channel mode of operation of the preferred embodiment of the present invention.

FIG. 21 shows information displayed in response to a user's request for supplemental programming information.

FIG. 22 shows programming, ordering and video promotional information displayed in a Pay-Per-View mode of operation of the preferred embodiment of the present invention.

FIG. 23 shows an ordering submenu used in conjunction with the mode of operation shown in FIG. 22.

FIG. 24 shows yet another ordering submenu used in conjunction with the mode of operation shown in FIG. 22.

FIG. 24A shows yet another ordering submenu used in conjunction with the mode of operation shown in FIG. 22.

FIG. 25 shows another grid listing of schedule information displayed in an All Listings mode of operation of the present invention.

FIG. 26 shows a Premium Services submenu that appears in one mode of operation of the preferred embodiment of the present invention.

FIG. 27 shows a Messages menu that appears in one mode of operation of the preferred embodiment of the present invention.

FIG. 28 shows exemplary messages used in connection with the menu of FIG. 27.

FIG. 28A is an alternative message menu.

FIG. 29 shows billing information used in connection with the menu of FIG. 27.

FIG. 30 shows a Key Lock Access menu that appears during one mode of operation of the preferred embodiment of the present invention.

FIG. 31 shows a menu appearing in connection with an Interactive Television mode of operation of the preferred embodiment of the present invention.

FIG. 32 shows information that appears in a Quote Watch menu in connection with the Interactive Television mode of operation shown in FIG. 31.

FIG. 33 shows other information that appears in connection with the Interactive Television mode of operation shown in FIG. 31.

FIG. 34 is a menu showing information that appears in a news display in the Interactive Television mode of operation of the preferred embodiment of the present invention.

FIG. 35 is a menu showing information that appears in a sports display in the Interactive Television mode of operation of the preferred embodiment of the present invention.

FIGS. 36A-36D illustrate a flow chart showing the operation logic required for implementation of a computer program for the electronic program guide.

FIG. 37 is a menu showing a Locator screen for locating channel numbers and defining favorite channel lists.

FIG. 38 is an alternative menu that can be used in a MENU mode of operation of the electronic program guide.

FIGS. 38A and 38B show, respectively, an alternative main menu screen and a listing-by-time screen accessible from the alternative main menu.

FIG. 38C is a second alternative menu screen including the "By Title" selection box.

FIG. 38D shows a screen of alphabetical listings displayed upon selection of the "By Title" option.

FIG. 38E illustrates the scroll mode of one embodiment of the "By Title" option of the present invention.

FIG. 38F illustrates the search mode of one embodiment of the "By Title" option of the present invention.

FIG. 39 is a Lockout menu that alternatively can be used for permitting or prohibiting access to certain programs.

FIG. 40 is a Setup menu that can be used to set text location and a purchase code for premium and pay-per-view programming.

FIG. 40A shows an exemplary menu for inputting a lockout code.

FIGS. 40B through 40E show, respectively, exemplary menus for entering, confirming, clearing or changing a purchase code.

FIG. 41 is a Lockout Verify menu that is used in connection with the Lockout menu of FIG. 39.

FIG. 42 is a flow chart showing the operation of the preferred embodiment of the textfit system of the invention herein.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

System Configuration

FIG. 1 is a block diagram showing various components of the electronic program schedule system generally designated as 10. Physically, these system components can be located in a user's set-top cable converter box or other signal reception or processing device, such as a satellite receiver. Alternatively, the components can be mounted in a separate housing, or included as part of a television receiver, VCR, personal computer, or multimedia player; or reside as a distributed application in a broadband network architecture.

An input signal 11 is connected to a receiver 12, which receives a transmitted data stream from a data provider. The data stream may contain, for example, information about programs or services available in a particular market, geographical or otherwise. The input signal 11 can originate, for example, as part of a standard broadcast, cablecast or satellite transmission, or other form of data transmission. The data provider is a program information provider, the satellite uplink manager, a local cable operator, or a combination of these sources, and the data stream contains program schedule information for all television programs and other services available in the operator's geographical market.

The data stream may be modulated and then transmitted on the cable line in any number of ways, including as part of a dedicated channel transmission operating at a frequency of, for example, 75 MHz. Those of skill in the art will

understand that numerous other transmission schemes can be used to transmit the data stream, such as embedding it in the vertical blanking interval of a program broadcast signal. As will be discussed in greater detail below, according to the present invention, the transmitted data stream may additionally contain application software for implementing or updating the electronic program guide at the user site.

The transmitted program schedule data or application software is received by the receiver 12 on signal input line 11. The received signal is passed from the receiver to a data demodulator 13, such as a QPSK demodulator or a GI Info-Cipher 1000R, which demodulates the transmission and passes it to a buffer 15.

A microcontroller 16, such as a M68000EC, receives data passed to the buffer 15. Bootstrap operating software, which may be used for capturing electronic program guide application software updates, is stored in a read only memory (ROM) 17. The microcontroller 16 uses the received program schedule information to build a database by storing the data in appropriately organized records in dynamic random access memory (DRAM) 18. The stored schedule information can be updated on a periodic basis, such as hourly, daily or weekly, or at any time when changes in scheduling or other factors warrant an update. The system also includes a system clock 19.

Alternatively, the program schedule information could be supplied in a ROM, disk or other non-volatile memory, or it could be downloaded to a storage disk or other data storage device. The invention herein is not directed to the particular method of transmission or reception of the schedule information.

If the microcontroller 16 recognizes the received data as application software which controls the program schedule system, as opposed to program schedule information, it stores it in non-volatile memory, such as an electrically erasable programmable ROM (EEPROM) 20 or battery-backed static RAM (SRAM). This configuration allows revised or replacement versions of the application software to be downloaded directly from the software developer to the user site through the cable or other transmission system.

In the case where an EEPROM is utilized, revised or replacement versions of the application software downloaded from the developer are first stored in DRAM 18 by the microcontroller 16, under direction of the downloading operating software stored in the ROM 17. The stored application software can then be checked for accuracy by, for example, a checksum analysis or other verification routine.

After the accuracy of the application software has been verified, the microcontroller 16 initiates a routine to re-program the EEPROM 20, where the application software is permanently stored. The microcontroller 16 will issue proper control commands to a reprogram circuit 21, which is adapted to supply the proper program voltage and logic control signals 22 required to erase and write to the EEPROM. It supplies this program voltage, Vprog, as well as any other required control signals, such as read or write enable, to the EEPROM 20 upon command from the microcontroller 16. After the EEPROM 20 has been electrically erased, the microcontroller 16 initiates transfer of the new application software from the DRAM 18 to the EEPROM 20 for storing.

When a battery-backed SRAM is utilized as non-volatile memory, the microcontroller stores the revised or replacement version of the application software downloaded from the developer directly in the SRAM, again under direction of the downloading operating software stored in the ROM. The

stored application software can then be checked for accuracy by, for example, a checksum analysis or other verification routine.

When power is first applied to the system 10, the bootstrap operating software verifies that the program guide application software is resident in memory. If it is not resident, the bootstrap operating software waits for a download of the software. Once the application software is resident, the microcontroller 16 executes the application program software from a dedicated portion of the DRAM 18. Alternatively, the application software can be executed directly from the non-volatile memory 20. Under control of the program guide application software, the microcontroller 16 first verifies that the program schedule information is resident in DRAM 18. If it is not resident, the microcontroller waits for a download of the program schedule information, as discussed above. Alternatively, if the application program is resident in memory, but the database records containing the program schedule information data are not yet available, the application software can be configured to carry out other tasks, such as allowing the user to carry out functions not requiring the program schedule information data, as well as displaying an appropriate message indicating the database data is not yet available.

When the schedule system is operating, as discussed in greater detail hereinbelow, the microcontroller 16 takes the program schedule information stored in the DRAM 18 and, in conjunction with other downloaded data types such as stored bit maps for the screen configuration and the graphic symbol or logo displays stored in non-volatile memory 20 or, alternatively, in DRAM 18, supplies it to a video display generator (VDG) 23, which in the present embodiment may be a commercially available VGA-type graphics card, such as a Roegen card manufactured by Rotelec. The VDG includes a standard RGB video generator 24, which takes the digital program schedule information sent by the microcontroller 16 and converts it to an RGB format in accordance with the bit map for the particular screen display then being presented to the user on the television receiver 27. The configuration of each screen is shown and discussed in greater detail in the System Operation section below.

The VDG also includes a Video Overlay Device 25, which accepts the RGB video input, as well as an input from conventional television tuner 28, such as a conventional tuner manufactured by General Instrument or a Jerrold DPBB tuner, which supplies a program signal in standard NTSC video format. The overlay device 25 converts and combines the RGB signal with the signal from the tuner 28, and produces a composite NTSC output signal containing both the program signal and the program schedule information, as shown in FIG. 2. This composite video signal is supplied to a modulator 26, shown in FIG. 1, which can be a modulator such as available from Radio Shack, and then to the television receiver 27, which the user keeps tuned to the modulated channel, for example, channel 3 or 4. The composite video signal can also be supplied directly to the television receiver 27 or other receiving device from the VDG through a video port 25A on the VDG.

The system components identified in connection with FIG. 1 can all be implemented in a preferred platform by, for example, an IBM personal computer equipped with a transmission link and a video graphics card, such as those manufactured by Rotelec. Other platforms, such as a cable converter box equipped with a microprocessor and memory, or a broadband network also could be used. Examples of the particular components are as follows: Microcontroller—Motorola part no. MC68331-16; ROM—Texas Instruments

part no. TMS27PC512; DRAM—Texas Instruments part no. TM4256; EPROM—Intel part no. 28F0018X-T. In any event, those of skill in the art will appreciate that the particular details of the hardware components and data storage are a function of the particular implementation of the system, and are not the subject of the present invention.

As discussed in detail below, the user may navigate through the program schedule system with a remote controller, such as that shown in FIG. 3, which operates on conventional principles of remote control transmitter-receiver logic, such as by infrared or other signalling, or other suitable user interface. The remote controller 31 communicates with the microcontroller 16 through the remote controller receiver 29, shown in FIG. 1, which can be a Silent Partner IR receiver and which receives signals transmitted by the remote controller 31 and supplies the microcontroller 16 with a corresponding digital signal indicating the key depressed by the user.

A remote controller suitable for the present invention, such as shown in FIG. 3, which can be a remote controller manufactured by Universal Electronics or Presentation Electronics' Silent Partner, may include a power switch 32, volume 33 and mute 34 controls, an ENTER or key 35, 0-9 digit keys 36, four direction arrow keys 37A and 37B, a MODE key 38 and an information key 39 that is designated with a lower case "i." The power 32, volume 33 and mute 34 keys operate in the same manner as conventional remote controllers typically used with present-day television receivers. The numeric digit keys 36 also function in much the same manner as conventional remote controllers. A brief description of the remaining keys follows.

The MODE key 38 takes the user through various layers of the electronic program schedule system 10 and generally allows the user to return to a previous screen when he is in a submenu. The up/down direction arrow keys 37A allow a user to navigate through the different TV program channels when the program schedule system is in a FLIP or BROWSE mode, as will be fully described below, and also allow the user to navigate through highlighted bars displayed on the TV screen when in a MENU mode. The left/right direction arrow keys 37B allow the user to navigate through selected time periods when the program schedule system is in the BROWSE mode, as will also be described below. They further allow the user to navigate across subject-matter categories while in the "Categories" submenu of the MENU mode, as well as to navigate across time periods when the program schedule system is in a pay-per-view ordering mode and, in general, navigate in left or right directions to select various icons and other objects. The information, or "i," key 39 allows the user to view supplemental program and other information during the various modes of the program schedule system. The ENTER 35 key fulfills and inputs a command once the user has made a selection from the remote controller keys. The function and operation of these keys will be made more apparent in the detailed discussion of the FLIP, BROWSE and MENU modes below.

A second embodiment of the remote controller 40 is shown in FIG. 4. This embodiment of the remote controller also includes a power key 41, numeric digit keys 42, direction arrow keys 43A and 43B, information key 48, ENTER or SELECT or "OK" key 44, volume control 45, lockout key 45A, mute keys 46 and help key 48A. It also includes pound sign and star keys.

This embodiment of the remote controller further includes a number of icon keys 47A and 47B, which correspond to different submenus or modes of the program schedule sys-

tem. The icons 47A and 47B may also be displayed on the TV screen when the program schedule system is operating. The icon keys essentially replace the MODE key 38 used in the embodiment of the remote controller shown in FIG. 3. Using these keys, the user can move from one mode to another simply by depressing the icon key corresponding to the desired mode of operation of the program schedule system. In the embodiment of FIG. 4, the icons 47A and 47B are shown as graphic symbols situated directly above a corresponding color-coded key. Alternatively, the color-coded keys could be eliminated and keys could be formed in the image of the icon itself.

The embodiment of the remote controller shown in FIG. 4 also includes three color-coded viewer preference or favorite channel keys, 48A, 48B and 48C that are situated directly above the icon keys. Each of these keys indicates to the program schedule system a distinct user-created "Channel Preference" or "Favorite Channel" list, which is a listing of a specific subset of channels for a particular user, arranged in the sequential order that the user wishes to view during operation of the program schedule system. The creation of the Channel Preference or Favorite Channel list is discussed in the following section. Thus, the system provides for at least three individual channel subsets for three individual users.

The remote controller of FIG. 4 also may be equipped with a "HELP" key 48A, which, when depressed, causes the microcontroller 16 to retrieve previously stored instruction messages from memory and cause them to be displayed on the television receiver 27. These messages offer help to the user in the form of instructions that guide the user through the operation of the various operating modes of the electronic television program guide. They may be text messages, or instructional video images, or audio programs, depending on the storage capacity of the system, or any combination of these. Moreover, these help messages may be created so that they are context-sensitive, i.e., the messages displayed depend entirely upon the precise point in the operation of the electronic program guide that the user depresses the help key 48A. For example, information could be supplied for operation of the remote controller, for operating the FLIP or BROWSE mode (discussed below), or any other mode of operation of the guide, for impulse ordering, for setting a lockout, etc. In order to accomplish this, each point of operation of the guide could be coded so that the microprocessor could track the current operating point, for example, by temporarily storing the code reflecting the present operating point as the user operated the guide. When the user pressed the help key 48A, the microcontroller 16 would retrieve an appropriate set of messages based on the presently stored operating point code. Additionally, the key 39 could be used to carry out the function of the help key.

Additionally, each of the functions of the remote controllers can also be integrated into a keypad on the user's cable box or other hardware.

System Operation

In operation, the electronic program schedule system of the present invention functions as follows.

FLIP Mode

When the user is viewing a particular program channel on the television receiver, the program schedule system defaults to a FLIP mode, shown in FIG. 5. In this mode, a graphic overlay 51 containing programming information for the channel currently tuned on the tuner is superimposed in

overlying relationship with a received program signal 55 on the screen of the television receiver 27 whenever the viewer changes the program channel, for example, by using the up/down direction arrows on the remote controller. The video overlay device 25, such as shown in FIG. 1, combines the computer-generated RGB video-graphic overlay information with the NTSC-format program signal from the tuner 28, and supplies an NTSC-format output signal, which includes the program signal from the tuner and the program schedule overlay information for viewing on the television receiver 27.

The programming information contained in the graphic overlay 51 is supplied to the RGB video generator by the microcontroller. In FLIP mode, the microcontroller first searches the program schedule database in, for example, the DRAM 18 to retrieve the programming information for the currently tuned channel 52 corresponding to the current time; i.e., the time at which the user just turned on the television receiver for viewing. The microcontroller 16 then supplies the current channel and program information to the RGB video generator 24 which converts the digital data information to RGB format and supplies it to the video overlay device 25.

In normal operation, the microcontroller 16 defaults to displaying all channels offered by the cable company prioritized by numeric order, which is determined by the broadcast channel position in the radio spectrum or the marketing judgments of local cable operators. Using a "Channel Preference" submenu, or an alternative "Locator" screen, both of which are discussed below, the user can revise the content and/or sequential order of the channels presented to the television receiver 27.

In general, if the user does not issue a change-channel instruction, or other command, from the remote controller 40 within a predetermined time interval while in the FLIP mode, the microcontroller 16 instructs the VDG 23 to remove the graphic overlay 51 from the television receiver, thus presenting only a program signal 55 to the television receiver 27 for viewing. The duration of the predetermined time interval is such that it allows the user sufficient time to read the programming information contained in the overlay. The duration of the predetermined time interval during which the graphic 51 overlay appears is stored in a location in non-volatile memory 20 addressable by the microcontroller 16. The user can change the duration of the time interval, by first entering a Viewer Preference mode, and then selecting an "overlay interval" entry. The microcontroller 16 then causes a user prompt to be displayed on the screen which, for example, asks the user to select an appropriate time period for displaying in the graphic overlay on the screen. Using the numeric keys, the user can input an appropriate response, for example, a period between 5 and 60 seconds, and then depress ENTER. The new interval period is then read and stored by the microcontroller 16 in the overlay time interval location in memory.

If the user issues a change-channel command from the remote controller 40 before or after the predetermined overlay period has elapsed, either by using the up/down direction arrows 43A, or by entering a desired channel number using the numeric keys 42 and then depressing the ENTER key 44, the microcontroller 16 will cause the tuner 28 to tune to the desired channel—either the channel immediately preceding or following the current channel when the up or down arrow 43A is used or the specific channel entered on the numeric key pad by the user—and will also search for and immediately cause to be displayed the current program information for that channel. Thus, as the user flips through

the channels, the program schedule information for any selected channel automatically appears in the graphic overlay 51 while the actual program 55 appearing on the selected channel at the particular time occupies the remainder of the screen.

The system can also be configured to issue an error message, such as an audible beep or displayed text indicating an invalid key stroke, if the user depresses either the left or right direction arrow keys while in the FLIP mode.

BROWSE Mode

To initiate the BROWSE mode, the user depresses the MODE switch once while in the FLIP mode when using the first embodiment of the remote controller 31 shown in FIG. 3. Utilizing the second embodiment of the remote controller 40 shown in FIG. 4, the user would depress the button below the BROWSE icon 47A.

In the BROWSE mode, the user is provided with the ability to scan through program schedule information for any channel, including, but not limited to, the channel being viewed, while at the same time continuing to view the TV program previously selected. As shown in FIG. 11, in this mode the graphic overlay information that appears in the FLIP mode is replaced with programming information for the channel being browsed, which may or may not be the channel currently being viewed by the user. After the user issues the command from the remote controller 40 to enter the BROWSE mode, a graphic overlay 111 is generated, as in the FLIP mode, with program schedule information for the currently tuned channel 112 and a textual BROWSE indicator 113 to remind the user of the currently active mode, as shown in FIG. 11.

If the user depresses either the up or down direction arrow on the remote controller 40 while in the BROWSE mode, program schedule information for either the prior or next channel is displayed in the graphic overlay portion 111 of the television receiver screen 27, while the tuner remains tuned to the channel program that appeared on the television receiver at the time the user entered the BROWSE mode, as shown in FIG. 12, and continues to so appear. Each successive depression of the up or down direction arrow key produces corresponding program schedule information for the selected channel. The graphic overlay may also include a small video window for showing the actual video signal of a currently aired program or a clip of a future program corresponding to the schedule information then appearing in the BROWSE overlay. In this way, the user can simultaneously scan program schedule information for all channels while continuously viewing at least one selected program on the television receiver. With the advent of sophisticated television receivers, it may also be possible to simultaneously display multiple broadcast programs on a single screen for viewing, or to split the screen to show, for example, broadcast programs in combination with advertisements. The BROWSE feature could be used in any of these situations.

If, at any time during scanning of the program schedule information in the BROWSE mode, the user desires to tune the television receiver 27 from the program channel currently being viewed to the program channel indicated in the schedule information in the graphic overlay, he simply depresses the ENTER button 44 and the tuner 28 will be tuned to that channel. If the user does not want to view another channel and wishes to exit the BROWSE mode, thus removing the graphic overlay 111 with the program schedule information, he must depress the MODE key twice in the

first embodiment of the remote controller 31. The first depression of the MODE key takes the user to the MENU mode, discussed below, and the second depression will take the user to the FLIP mode. Once in the FLIP mode, the graphic overlay will be removed after the duration of the time-out interval has passed. In the second embodiment of the remote controller shown in FIG. 4, the user toggles the BROWSE icon key to deactivate the BROWSE mode.

When the user first enters the BROWSE mode and begins scanning channels, the schedule information appearing in the overlay portion 111 describes the programs currently playing on any particular channel. In order to view programming information for later or earlier times, the user employs the left and right direction arrows 43B. As a consequence, the system will display future program schedule information for the particular channel previously selected by the up and down direction arrows, whether it is the channel currently being viewed or any other available channel. The schedule information presented includes the name of the program and program start/stop time. The instant embodiment of the system, in order to conserve memory, will not allow the user to view programming information for a time prior to the current time. The system could be easily modified to provide such information if adequate memory is made available. It may be desirable, for example, to allow a user to view schedule information for an earlier time to find a particular show and then allow the user to command the microcontroller to find and display future airing dates of the show, or the microcontroller could simply do this automatically.

When viewing program schedule information for a future time in the BROWSE mode, the displayed time of airing 121 of the particular show 122 is highlighted, as well as the channel number and service indicator 123, as shown in FIG. 12A. Such highlighted information reminds the user that he is viewing program schedule information for a future time. Also, when viewing program schedule information for a future time on any particular channel in the BROWSE mode, depression of the channel up direction arrow key on the remote controller 40 causes programming schedule information for the next channel to appear, which corresponds in time to the future time that was being viewed before the up key was depressed by the user. The channel down direction arrow key 43B functions identically in this mode.

If while viewing program schedule information for a future time in BROWSE mode the user depresses the ENTER key on the remote controller, the microcontroller 16 will instruct the VDG 23 to display a REMINDER overlay message 130 which, as shown in FIG. 13, is displayed as a second overlay 131 appearing above the BROWSE overlay 132. The REMINDER message 130 queries the user as to whether the system should remind the user, at a predetermined time before the start of the selected program, that he or she would like to view the selected program, as shown in FIG. 13. If the user responds affirmatively, the microcontroller 16 stores reminder data consisting of at least the channel, time and day of the selected program in a reminder buffer, which contains similar schedule information for all programs for which the user has set a reminder. At a pre-determined time before the selected program start time, for example, five minutes, the microcontroller 16 will retrieve schedule information, including title and service, based on the reminder data, and will instruct the VDG 23 to display a REMINDER overlay message 140 on the television receiver 27, as shown in FIG. 14, to remind the user that he or she previously set a reminder to watch the selected program. The REMINDER message 140 contains the channel, service and start time. It also displays the number

of minutes before the time of airing of the particular show and updates the display every minute until the time of airing. The REMINDER message 140 also displays a "TUNE" inquiry, which asks the user if she would like to tune to the selected program. When the user sets multiple reminders, the reminder overlays are stacked, for example, in ascending order according to the time each reminder is scheduled to be displayed, and the next reminder message will appear on the television receiver after the user takes appropriate action to remove the reminder message then being displayed. The REMINDER message (140 could also be adapted to allow the user to display or modify a list of all reminders previously set by the user. As with the overlay display time period in the FLIP mode, the user can modify the time period before a selected program that the REMINDER message appears by entering the Viewer Preference mode and revising the time entry.

MENU Mode

Using the remote controller 31 shown in FIG. 3, the user can enter the MENU mode from the BROWSE mode or from the FLIP mode by toggling the MODE button 38 once or twice, respectively. Using the remote controller 40 of FIG. 4, the user would simply depress the key 47B corresponding to the MENU icon.

Referring to FIG. 6, in the MENU mode, the system displays a plurality of menu items and icons, which correspond to and allow user selection of distinct program schedule information display formats, local cable system message boards and other on-line information services. The MENU screen shown in FIG. 6 is a full-screen display. In the embodiment shown in FIG. 6, there are four vertically selectable horizontal bars 61-64, which are accessed using the up and down direction arrows 43A on the remote controller 31 or 40. At the extreme left of each bar, an identifying icon 61A-64A is displayed, which identifies the information contained in that bar. In the embodiment of FIG. 6, the "TV GUIDE" icon 61A in the first bar corresponds to program schedule information from TV Guide® magazine, the "NOW SHOWING" icon 62A in the second bar 62 corresponds to pay-per-view and premium service events, the "MSO Logo" icon 63A in the third bar 63 corresponds to Customer Service or local cable company information messages, and the circular icon 64A in the fourth bar 64 corresponds to other interactive services available to the user, or in the case of broadband networks, other venues, e.g. home shopping, banking or telephone use. As also shown in FIGS. 6 and 6A, each bar also contains a textual description of its contents.

When the user first enters the MENU mode, the system defaults to selection of the program schedule bar. When a particular bar is selected, the textual description is removed and a plurality of icons or identifying windows are displayed adjacent the identifying icon. In FIG. 6, the program schedule bar 61 is selected. Using the up or down direction arrow key on the remote controller 40, the user selects a vertically adjacent bar. FIGS. 15-17 show, respectively, selection of the Pay-Per-View bar 62, the Customer Service or Messages bar 63 and the Interactive TV services bar 64.

An alternate MAIN MENU screen 215 is shown in FIG. 38. Certain selection screens accessible from the menu shown in FIG. 38 are shown in FIGS. 38A and 38B. It has three horizontally selectable bars: program schedule 205, Home Theater 206 and Customer Service 207. The MAIN MENU screen 215 also contains an additional "Locator" identifier, which is described below.

A second alternate MAIN MENU screen 320 is shown in FIG. 38C. The MAIN MENU screen of FIG. 38C includes a "By Title" selection box 321 in addition to the "By Time" 322 and "By Channel" 323 selection boxes.

Once a particular bar in the MENU screen is selected, the user can select a particular icon from the plurality of horizontally selectable displayed icons 65A-65C by using the left or right direction arrow and the ENTER key on the remote controller 40. Each icon contains a graphical symbol appearing in a background window of a particular color. When a particular icon is selected, it is offset from its background window and the color of the window changes. In FIG. 6, the grid icon 65A immediately adjacent the "TV GUIDE" icon in the first bar 61 is selected.

The function corresponding to the selectable entries in the MAIN MENU screen will now be discussed with reference to FIG. 6. It will be appreciated by those of skill in the art that the same functionality applies in the categories shown in the MAIN MENU 215 shown in FIG. 38.

In the uppermost vertically selectable horizontal bar 61, the first grid icon 65A represents an "All Listings" mode in which the program schedule information is displayed in a grid listing, such as that shown in FIG. 18. Alternatively, a single column grid-like display could be used, as that shown in FIG. 25. In this format, the vertical y-axis identifies the channel number and service while the horizontal x-axis identifies the time. The screen display of FIG. 18 also contains in the upper left-hand corner a mode identifier 180, in this case the notation "All Listings," to remind the user of the current operating mode of the system. Directly underneath the mode display is a highlighted display 181 of the channel that the user was watching before entering the MENU mode. In the upper right-hand corner, a logo icon 182 appears in a window directly above a date/time identifier 183, which alternatively displays the current date and time.

In the center of the screen display shown in FIG. 18 is a graphical Active Key Display (AKD) 184 which indicates to the user those keys on the remote controller that are active for that particular mode of the program guide display system. For example, in the screen display of FIG. 18, the cursor can only move up, down or to the right. If the user were to depress the left direction arrow key on the remote controller at that point, the system would not carry out any function since the cursor can not move to the left. Thus, the left arrow key is not active so its image is not displayed on the AKD 184. Similarly, since the system will only respond to a depression of the up, down or right direction arrow keys and the ENTER key, they are the only key images displayed on the graphical AKD 184. The MODE key, though not displayed, is always active to change from one mode to another. When the user first enters the All Listings guide, the time listing begins by default at the half-hour immediately preceding the current time unless the current time is on the hour or half-hour, in which case the display begins with the particular hour or half-hour, and the channel listing begins at the last channel being viewed by the user before entering the MENU mode. For example, in FIG. 18, the current time is displayed as 7:13 p.m., the time listing begins at 7:00 p.m. and the channel listing begins with channel 4.

In the All Listings mode, a moveable highlighted cursor 185 is used to indicate the currently selected program to the user. The user manipulates cursor movement using the direction arrow keys on the remote controller 40. Furthermore, the entire information display pages upward if the cursor is placed at the bottom of the screen and the down

direction arrow is depressed, and similarly pages to the left if the cursor is at the extreme right side of the display and the right direction arrow is depressed. In this way, the user can navigate through the entire program schedule.

The folder icon 65B immediately to the right of the All Listings icon in the top horizontal bar 61 of FIG. 6 identifies a "Category Listing" mode in which program schedule information is displayed and categorized by program content, as shown in FIG. 19. The particular listing shown in FIG. 19 includes the categories of Movies, Sports, News and Children 190A-190D. The database record stored for each listing contains a content-specific identifier so the microcontroller can search the database and categorize the information by content for purposes of displaying it in the Category Listing mode. As shown in FIG. 19, the user can manipulate the cursor left or right to highlight any one of the categories which appear at the head of the listing. In FIG. 19, the "Movies" category 190A is selected. As shown, the user is given a display of all movies, prioritized by time and then alphabetically by title of show, beginning with the half-hour immediately preceding the current time unless the current time is on the hour or half-hour, in which case the display begins with the particular hour or half-hour. The screen display shown in FIG. 19 also includes a textual description of the current operating mode of the program schedule system, as well as the graphic AKD 184, similar to that used in connection with the All Listings mode.

As with the All Listings mode, if the user highlights a show which is currently airing, he can immediately tune to that show by depressing the ENTER key on the remote controller 40. If the highlighted show is one that will appear at future time, the user is again given the option of setting a REMINDER message.

The triangular icon 65C at the far right of the TV GUIDE bar 61 in the display of FIG. 6 identifies a "Channel Listing" mode in which the program schedule information is categorized and displayed by channel, as shown in FIG. 20. The screen display shown in FIG. 20 again includes a textual mode identifier 201, the graphic AKD 184, and the window including the logo icon 182 and alternating time/date display 183. At the head of the program listing is a list of several consecutive channels 202A-202C beginning with the last channel viewed by the user before entering the Channel Listing mode. The channel in the middle window 202B is highlighted and is the channel for which schedule information is displayed. The display identifies those programs appearing on the highlighted channel beginning with the half-hour immediately preceding the current time unless the current time is on the hour or half-hour, in which case the display begins with the particular hour or half-hour. The user can display further future listings by manipulating the cursor to the bottom of the screen and paging the display, as previously described. The user can also change the selected channel by manipulating the left or right direction arrow keys on the remote controller 40. When the user issues a change-channel command in this manner, the next consecutive channel will be displayed in the highlighted window 202B in the channel string at the head of the display, and schedule information for the newly selected channel will be displayed on the television receiver 27.

As with other modes, if a user wishes to tune to a highlighted program that is currently airing, he can do so by simply depressing the ENTER key on the remote controller 40, and if the user wishes to view a program that airs at a future time, the user is again given the option of setting a REMINDER message. In each of the FLIP, BROWSE and MENU modes, a lower case "i" icon appears at a number of

occasions in connection with certain program listings, such as movies, such as the "i" 203 shown in FIG. 20. Any time this icon appears, the user can view additional programming information, generally comprising a textual description of program content and/or other information related to the program, such as the names of cast members and the like, by depressing the "i" key 48 on the remote controller 40. An example of a display of such additional information is shown in FIG. 21. The second horizontal bar 62 appearing on the screen in the MAIN MENU mode shown in FIG. 6 is the "Home Theater" Listing. It corresponds to Pay-Per-View events or services, specialized programming, and Premium Service programs. When this category is chosen by the user, the television receiver displays information as shown in FIG. 15. The first theater-ticket icon 150 that appears in this Home Theater bar identifies a format in which the Pay-Per-View events and premium services are displayed, as shown in FIG. 22. As with other modes, the user can manipulate the cursor to highlight and select any particular show. Also, the user can obtain additional information about the Pay-Per-View event or service by depressing the "i" key 48 on the remote controller 40. The Pay-Per-View menu screen display shown in FIG. 22 also includes a video display section 220 in which short promotional clips of current and future events and services can be shown to the user while the user is viewing the Pay-Per-View scheduling information. The display of FIG. 22 is bit mapped such that the advertising clips may be shown in the lower left quadrant of the screen. The clips may be shown randomly in the video display section 120 or, alternatively, the clip shown could correspond to the particular selected entry on the list of events, and would change automatically as the user navigated through the list.

When a user highlights a Pay-Per-View event or service by manipulating the cursor to the desired event or service using the direction arrow keys on the remote controller 40, he can order the event or service by depressing the ENTER button on the remote controller, thus linking schedule, promotional and ordering functions. If the user selects a particular Pay-Per-View event or service in this manner, the programming schedule system will next present to the user a Pay-Per-View ordering screen such as that shown in FIG. 23. The display includes a figure representing the cost of the event or service. The display also asks the user to choose from among a plurality of scheduled airing times 230A-230C, as well as whether the user would like to see a REMINDER message prior to the start of the Pay-Per-View event or service. The user responds to these inquiries by using the direction keys on the remote controller 40 to manipulate the cursor to the proper response and then depressing the ENTER key. After the user has ordered a Pay-Per-View event or service, the program schedule system will present the user with two ordering confirmation submenus, such as shown in FIGS. 24 and 24A. In either of these submenus, the user can confirm or cancel the Pay-Per-View event or service.

If the user confirms the order, the microcontroller 16 stores the Pay-Per-View ordering information in a location in memory. The ordering information can then be transmitted to the cable operator by the microcontroller 16 either by phone line or on the cable line where the system has two-way communication or other such interactive capability. Alternatively, a computer at the cable operator location can interrogate the memory where the microcontroller stored the Pay-Per-View ordering information. At the appropriate time, the cable operator supplies the Pay-Per-View event or service and it is received by all users who have ordered the program.

The second icon 151 in the Pay-Per-View bar of FIG. 15 identifies a specialized broadcast, cable or satellite programming service to which the user has access via the electronic program guide. In this mode, the electronic program guide application software acts to connect the user, through an appropriate data transmission link, to the programming service, at which point the user interacts with the service. Alternatively, the electronic program guide provides the navigation software, including the menus and scheduling information, for the particular programming service. Such a service could be, for example, Your Choice TV ("YCTV"), a service offering reruns of highly rated broadcast and cable programs, in which case the icon may take a form suitable to identify YCTV. The programming available on YCTV is then supplied to the user via the programming guide system.

The last icon 152 appearing in the Pay-Per-View bar of FIG. 15 identifies a display format which lists all Premium Services offered by the cable operator, as shown in FIG. 26. In this mode, the user can select for impulse ordering any one of the premium services by manipulating the cursor using the direction arrow keys on the remote controller and depressing the ENTER key. Similar to Pay-Per-View ordering, the system will present the user with a series of ordering displays and, if a service is ordered by the user, it will confirm the user's request using another other submenu. If confirmed, the microcontroller 16 will store the ordering information or transmit it directly to the cable operator. Once the order has been confirmed, the microcontroller can immediately allow the user access to the ordered premium service. In this manner, the user can order premium events or services on demand.

If, during FLIP or BROWSE modes, a user views a channel or schedule information for a service not subscribed to by the user, the microcontroller 16 causes an ordering submenu to appear instead of displaying a program signal along with the graphic overlay, as shown in FIG. 9. This submenu indicates to the user that she does not currently subscribe to the selected service, and then asks the user if she would like to order the service. If the user responds affirmatively, the program schedule system takes the user to the ordering submenu discussed above. In this manner, the user can order premium events or services on impulse.

The third horizontal bar 63 in the MENU mode shown in FIG. 6 is the "Messages" or "Customer Service" listing. As shown in FIG. 16, the first envelope icon 160 represents message information available from the cable operator. When the user selects the message icon, he is presented with a screen display of currently available messages, as shown in FIG. 27. The display shown in FIG. 27 includes cable system messages 270 and billing information 271. If the user selects the cable system messages option 270, she is presented with a message pertaining to the local cable operator, such as that shown in FIG. 28. If the user selects the billing status option 271 shown in FIG. 27, she is presented with a display of current billing information, such as that shown in FIG. 29. This information may include a history of purchases charged to the user, current balance information, pending orders, and an indication of available credit, which can be an authorized debit limit previously arranged with the cable or other operator. Thus, a user could specify only a certain pre-set spending limit. Once the amount of charges from pay-per-view events reaches the limit, the microcontroller would not permit further ordering of events. An alternative messages menu is shown in FIG. 28A.

The next icon 161 in the Customer Service information bar 63 of FIG. 16 identifies a "Viewer Preference" mode, which allows the user to create or revise a number of

program schedule system operating parameters. Once selected, this display presents the user with several preference options concerning certain operating parameters of the program schedule system, as well as the viewing of certain channels and/or certain content-specific programming, for example, those shown in FIG. 7.

The first option shown in FIG. 9 is the "Parental" option 70, which can also be expressed as a "Key Lock Access" option. Once this option is initially selected by the user, the system displays a "Key Lock Access" submenu such as that shown in FIG. 30.

The Key Lock Access menu shown in FIG. 30 allows the user to control access to individual channels and programs or events by requiring the user to enter an access code "key," consisting of a user-specified four digit code in the specific embodiment discussed herein, before ordering or viewing these pre-selected channels, programs or events. The menu display shown in FIG. 30 shows a series of subject categories that are entries in the vertical y-axis selectable by the user. A particular subject category is chosen by using the up or down direction arrow keys on the remote controller 40 to highlight the desired entry. Once the user selects a particular subject category, the left and right arrow keys are used to navigate within the chosen category.

The first subject entry shown in FIG. 30 is the "Parental Guidance" category 301. Once the user selects this category by manipulating the cursor to highlight the entry, the cursor can be then moved horizontally to an active window 302 which displays and selects one the five letter rating items in the category. The letter items represent ratings of program content as follows: "V" for violence, "N" for nudity, "L" for language, "AS" for adult situations and "PD" for parental discretion. Once the user selects a particular item, such as "L", by moving to the active window 302 using the right direction arrow key, depressing the ENTER key will indicate to the microcontroller 16 that a key lock access has been selected for programs rated with a "L" rating for violent or explicit language. The system indicates activation of a key lock access by displaying a key icon directly below the "L" category display. Once a key lock access is set, it can be deactivated by selecting the category letter and then depressing the ENTER key. This action causes the key icon to disappear. The user can change the rating category in the active window 302 by using the left or right direction arrow keys on the remote controller 40, images of which are displayed on the screen adjacent the active window as a reminder to the user. In this manner, the user can select other rating categories for setting a key lock access for any of the program content identifiers appearing in the Parental Guidance category.

The key lock access code itself consists of a four digit code, which the user can enter and modify at any time. To do so, the user highlights the fourth vertically selectable entry "Change Key Lock Access Code," 304 by manipulating the cursor to highlight it using the direction arrow keys on the remote controller. Once highlighted, the user enters a new four digit code or revises the then existing code and depresses the ENTER key. The microcontroller 16 then identifies the new four digit key lock access code and stores it in memory. The user can clear the key lock access code, as well as all other previously activated keys, by moving to the last entry in FIG. 30, "Clear Key Lock Access Code and All Keys," 305 which highlights the "OK" window, and then depressing the ENTER key. This action clears and deactivates all previously set keys, as well as the key lock access code.

The schedule information database record for each program contains a field that corresponds to the program

content identifiers in the Parental Guidance category. During operation, the microcontroller checks this field in response to a user command to tune to or order a program, or to display its corresponding schedule information before carrying out the tuning, ordering or displaying function. If the parental guide identifier in the program schedule information database record matches any one of the activated parental guidance identifiers shown in FIG. 30, the user will be prompted to enter the four digit key lock access code before the system takes any further action. If the entered code matches the key lock access code previously entered and stored by the user as described above, the system will carry out the user request to tune to the program, to order it, or to display its corresponding schedule information. If the code is not recognized by the system, no further action will be taken and the user's request will be denied.

By manipulating the cursor using the direction arrow keys to highlight the second entry, "MPAA ratings," 308 the user can also set a key lock access for programs based on their MPAA rating code, as also shown in FIG. 30.

As with the Parental Guidance category, once the MPAA rating category has been selected, the user can move horizontally within the category to the active window 306 to select one of the five rating codes, i.e., "G" for general audiences, "PG" for parental guidance, "PG-13" for suggested parental guidance, no one under 13 admitted without an adult, "R" for restricted and "X" for x-rated. As with the Parental Guidance category, by selecting a particular rating—by using the left or right direction arrow keys until the particular rating code appears in the active window—and then depressing the ENTER key, the user sets a key lock access for the rating, in which case a key icon appears below the rating code. And, as with the Parental Guidance category, once a key lock access is set, the system will prompt the user to enter the four digit key lock access code anytime a request is made to tune to, order or display schedule information for a particular program having a rating code which matches a rating code for which key lock access has been activated.

The Key Lock Access mode also includes a subject category 303 for controlling access to channels, which may be entitled, for example, "Channel Block" or "Channel Lock." As with the Parental Guidance 301 and MPAA 308 categories, the user navigates to the Channel Block category 303 by manipulating the cursor using the direction arrow keys on the remote controller and depressing the ENTER key. Once the Channel Block category 303 has been entered, the user can move horizontally to an active window 307, which in FIG. 30 indicates channel 2. Once the user highlights this window by manipulating the cursor using the direction arrow keys on the remote controller 40, a key lock access can be set for the channel appearing in the active window. This is done, as with the other subject categories in the Key Lock Access mode, by depressing the ENTER key, which again causes a key icon to appear below the channel number in the active window. The user can move to the prior channel or to the next channel in sequence by depressing either the left or right direction arrow key on the remote controller 40. In this manner, the user can activate a key lock access for any available channel.

As with the Parental Guidance 301 and MPAA 308 categories, once a key lock access is set for a particular channel, the system will prompt the user to input the key lock access code prior to carrying out an instruction to tune to or order that channel. If the input key lock access code matches the previously stored access code, the user's instruction is carried out. Otherwise, the user's instruction is ignored. Thus, the user can control access to the audio and

video program content of any available channel. In this instance, the microcontroller 16 will not allow audio or video program signals to pass to the VDG, but it will allow schedule information to appear for the channel.

An alternative method for effecting lockout of programs is accomplished using a "Lockout" screen, as shown in FIG. 39. In addition to limiting access to programs based on the Parental Guidance, MPAA and channel criteria, as discussed above, access may be limited on the basis of program title. FIG. 39 shows an alternative Lockout screen 250 that can be used to permit or limit access to programs based on program title, in addition to the aforementioned criteria. Other parameters also may be included, such as time of day, day of week, credit limit, and content category (e.g., talk shows).

To enter the Lockout screen 250 shown in FIG. 39, the user must enter a multi-digit lockout code using the numeric digit keys 42 and the enter key 44 on the remote controller 40. The lockout code is set initially when the system is first used or installed. To set a lockout code in the first instance, the user accesses a Setup screen 260, such as that shown in FIG. 40. The Setup screen 260 will automatically appear the first time the electronic program guide is installed and initialized. For access during normal operation of the electronic program guide, a suitable access path to the Setup screen 260 may be provided, such as from an appropriate icon in the MAIN MENU 215.

In the Setup screen 260 of FIG. 40, the user can navigate to the Lockout Code category 265 and set a new lockout code using the appropriate navigation and selection keys on the remote controller 40. A suitable menu for inputting the lockout code is shown in FIG. 40A. Once enabled, the lockout code must be used to set or modify locks, to view a previously locked program, or to clear or change the lockout code. The memory location of the stored lockout code also should be remotely accessible, such as by the local cable company, in case the user forgets the lockout code and it must be erased.

Once the lockout code is entered and the Lockout screen 250 of FIG. 39 is displayed, navigation within the screen is controlled by the direction keys 43A and 43B on the remote controller 40. Using the up and down direction keys 43A to move the selection cursor, either the Movie Rating 251, Parental Guidance 252, Channel 253, Locked Program 254 or Lockout Code 255 category can be selected. The left and right direction keys 43B are then used to navigate inside the selected category.

Clearing a previously set lockout code is accomplished by moving the selection cursor to the "Clear" entry 256 in the Lockout Code category 255 and depressing the enter key 44 on the remote controller 40. This causes the microcontroller to clear the lockout code stored in memory, as well as all locks previously set by the user. To change the current lockout code, the user navigates to the "Change" entry 257 in the Lockout Code category 255 and depresses the enter key 44 on the remote controller 40. The user is then prompted to enter a new lockout code, which is subsequently stored in memory by the microcontroller.

To set a lock in either the Movie Rating 251 or Parental Guidance 252 category, the user navigates to the selected entry in FIG. 39 by manipulating the selection cursor using the direction keys 43A and 43B on the remote controller 40, and then depresses a lockout key on the remote controller, such as the padlock key 45A shown in FIG. 4. The microcontroller will appropriately modify the display to indicate that a lock has been set, for example, by changing the color of the text or the background in the selected entry window,

or by displaying an appropriate icon next to the text in the selected entry window. In FIG. 39, a padlock icon 258 appears in the window of the "PG" entry in the Movie Rating category 251. Toggling the lockout key while the selection cursor is positioned on a selected entry will alternately enable and disable the lockout function for that entry.

Similarly, to set a lock for a particular channel, the user selects the channel using the selection cursor and then depresses the lockout key. In FIG. 39, the channel "4 KCNC" entry in the Channel category 253 has been locked, which is indicated by the inverse video and padlock icon appearing in the window.

Program locks also may be set by title, which can be effected in several ways. For example, when the above-described FLIP or BROWSE mode of the electronic program guide is enabled, thereby causing the title of a program to be displayed along with other program schedule information in a window superimposed on the actual program signal then being received, the user can limit access to the program corresponding to the displayed program information by depressing the lockout key 45A on the remote controller 40. The user also may limit access to the currently tuned program by depressing the lockout key 45A on the remote controller 40 while viewing the program, regardless whether the FLIP or BROWSE modes are enabled. In this instance, the microcontroller first removes the program signal from the display and then accesses the schedule information database record for the program then appearing and sets an appropriate flag to indicate the program has been locked. Also, when viewing program schedule information in the grid or category listings, as discussed above and shown, for example, in FIGS. 18-20, the user also can tag a program for lockout by highlighting it with the selection cursor and then depressing the lockout key 45A on the remote controller 40.

In each of these instances, the microcontroller then stores the program title in a lockout title list stored in memory along with any other titles that previously have been locked out by the user. Individual items in the lockout title list are displayed in alphabetical order in the "Locked Program" window 259 shown in FIG. 39, and the user may scroll through the list by positioning the selection cursor on the Locked Program window 259 using the up and down direction keys 43A on the remote controller in FIG. 40 and then using the left and right direction keys 43B to scroll through the list one item at a time. In order to save memory space, alternatively, the microcontroller may be programmed to set a flag or otherwise mark the particular database record containing the program schedule information for the program that is to be locked out, and to thereafter access the database to retrieve the title information when it is to be displayed, such as when the viewer is reviewing the lockout title list in the Locked Program window 259.

Once an individual title has been locked out, the microcontroller can be programmed optionally to display an appropriate lockout icon, such as a padlock, whenever program schedule information for the locked program is to be displayed, such as in the window overlay of the FLIP or BROWSE mode, or in the various grid and category displays available in the MAIN MENU displays. The system also may display an appropriate text message if someone tries to access the program signal of a previously-locked program. Of course, once a program is locked, in all instances the microcontroller prevents access to the actual program signal (including both the audio and video portions of the program signal) until an appropriate code is entered or the lockout is removed.

Several methods can be used to block programs at their time of airing. For example, in the case of the Movie Rating, Parental Guidance and Channel categories, the schedule information database record for each program is provided with a field that corresponds to the rating, program content identifier or channel appearing, respectively, in the Movie Rating 251, Parental Guidance 256 and Channel 253 category of the Lockout screen 250 shown in FIG. 39.

During operation, the microcontroller checks the appropriate field in the database record in response to a user command to tune to or order a program before carrying out the tuning or ordering function. Additionally, the lockout code also may be used to restrict access to program schedule information. In this instance, the microcontroller also would check the appropriate field in the schedule information database record before displaying schedule information for a program.

If the movie rating, parental guidance or channel identifier in the program schedule information database record matches any one of the locked-out entries indicated in the Lockout screen 250, a Lockout Verify screen 300 is displayed in overlaying relationship with the video signal then being displayed on the television receiver, as shown in FIG. 41. The user will be prompted to enter the previously set lockout code before the system takes any further action. As an added security measure, asterisks will be displayed as the user enters the lockout code. If the entered code matches the lockout code previously entered and stored by the user as described above, the system will carry out the user request to tune to or order the program, or to display its corresponding schedule information. If the code is not recognized by the system, no further action will be taken and the user's request will be denied. In this case, the Lockout Verify screen 300 will remain displayed on the television receiver waiting for a correct code to be entered. If no action is taken by the user, the Lockout Verify screen 300 will be removed after a predetermined time-out period, such as one or two minutes.

Similarly, in the case of lockout by title, the microcontroller also could check the title field in the schedule information database record and compare it with the list of program titles for which the user previously set a lock. If, as described above, the microcontroller does not maintain a list of the actual titles of programs locked by title, a suitable identifier can be set in a field in the database record to indicate that a program has been locked by title when the user first sets the lock, and, thereafter, the microcontroller could check that field in response to a user request to tune to or order a program, or display schedule information.

An alternative method for effecting lockout involves the use of a portion of the real-time program signal being received by the television receiver. With this method, codes corresponding to a program's rating, parental guidance category, title or channel are inserted into and transmitted along with the program signal, such as in the vertical or horizontal blanking intervals, or on raster scan lines that are not visible on the television receiver. When the program signal is received, these codes are stripped from the program signal and stored in memory. Methods and apparatus for the insertion transmission and reception of digital codes carried on a program signal are known in the art.

After the transmitted codes have been separated from the program signal and stored in memory, the microcontroller can compare them with the lockout criteria set by the user in the Lockout screen and take appropriate action, as described above.

The Setup screen 260 shown in FIG. 40 also contains a Purchase Code category 270, which allows the user to set a numeric purchase code that must be entered before any premium channels or pay-per-view programs can be ordered. The Setup screen 260 shown in FIG. 40 includes entries for setting a new purchase code and for clearing or changing a previously set password. Appropriate menus for setting, confirming, clearing or changing the purchase code are shown in FIGS. 40B through 40E. Once a user sets a purchase code, the microcontroller thereafter will display a Purchase Code Verify screen in response to a user request to tune to or order a premium services channel or pay-per-view program. The Purchase Code Verify screen works in a manner similar to the Lockout Verify screen 300 in that the user is prompted to enter the previously set purchase code password before the microcontroller will tune to or order the requested program. If the correct purchase code is not entered, the microcontroller will take no further action and the Purchase Code Verify screen will remain displayed waiting for input of the correct code. If no action is taken within a predetermined time-out period, the Purchase Code Verify screen will be removed.

The next option shown in FIG. 7 is the Channel Preference or "Favorite Channel" list option 71. By highlighting this icon and depressing the ENTER key on the remote controller 40, the user is presented with a submenu on the screen such as that shown in FIG. 8.

In normal operation, the program guide system presents channels to the user in numerical order in response to an up or down change-channel command issued by the user using one of the direction arrow keys on the remote controller. The channel number presentation sequence includes all channels offered by the cable company in the order of which they are modulated onto the channel by the operator.

The program guide system also provides the capability of selecting from among several user-defined channel presentation sequences, which are activated using one of the three "check mark" icon keys 48A, 48B or 48C on the remote controller 40 shown in FIG. 4. Each of these keys represents a preferred particular list of channels which a particular user selects and which the microcontroller stores in memory as a "Channel Preference" list, as discussed in detail below. To activate one of these preferred channel lists, the user depresses the corresponding check-mark icon key, in which case the microcontroller may display the chosen icon on the screen in the graphic overlays and full screen displays to remind the user that a particular channel preference list is being used by the system. Once a preference list is activated, the system will limit the tuning of the television receiver and the display of schedule information only to those channels that are designated in the activated viewer preference list.

To revise the content and/or sequential order of the channels in the Channel Preference list, the user enters the MENU mode of the programming guide system. To enter the MENU mode from the FLIP mode, the user twice depresses the MODE key 38 when using the remote controller 31 of FIG. 3. To enter the MENU mode when using the alternative embodiment of the remote controller 40 of FIG. 4, the user simply depresses the MENU icon key 47B.

When first entered, the MENU mode has a screen display such as shown in FIG. 6. To select the submenu for editing the Channel Preference list, the user first selects the third horizontal bar 63, which can be titled, for example, "Messages" or "Customer Service," by manipulating the cursor using the down direction arrow key, as shown in FIG. 7. The screen of FIG. 6A is thereby displayed. The user then selects

the second icon 161 appearing in that bar, indicated with a check mark, which corresponds to a "Viewer Preference" mode, by highlighting the icon using the direction arrow keys and again depressing the ENTER key. This action will cause the microcontroller 16 to display a Viewer Preference submenu such as that shown in FIG. 7. By selecting the Channel Preference or "Favorite Channel" entry 71, the user enters the Channel Preference submenu, shown in FIG. 8. If the user has not already done so, he would then depress the particular check-mark icon key on the remote controller 40 of FIG. 4 to create or revise the particular channel preference list.

In the Channel Preference menu shown in FIG. 8, a list 80 of all channels available on the particular cable system is displayed on the left side of the television receiver screen, labeled "Choices" in FIG. 8, and the viewer's preferred list 81, designated "Selected" in FIG. 8, is displayed on the right side. If a particular code, such as an FND or "-1" symbol appears in the first (uppermost) position 82 of the viewer preference list 81, the system displays information for all channels in numerical order in all modes of operation. This is the default mode of the system.

By selecting channels in sequence from the available list 80 and placing them in the desired order in the preference list 81, the user can select a subset of channels and/or rearrange the default sequence in response to a channel up or channel down command from the user. This is accomplished by highlighting a channel in the available list 80 using the up and down direction arrow keys on the remote controller 40 and depressing the ENTER key 44, which stores the entry temporarily in a buffer.

The microcontroller 16 stores a list of all channels previously entered in the viewer preference list 81. As a particular channel is highlighted by the user when navigating through the available channel list 80 displayed on the left side of the television screen, a window 84 appears adjacent to the particular channel highlighted by the user. If the particular channel already appears in the viewer preference list 81, the system displays a "DELETE" message in the window 84 as a reminder that the channel was previously selected from the available channel list 80 and can only be deleted from the list 81, which is accomplished by depressing the ENTER key 44. If the particular highlighted channel in the list 80 was not previously selected, the system displays a "SELECT" message in the window 84 as a reminder that the particular channel will be selected for addition to the viewer preference list 81 if the user depresses the ENTER key 44. The microcontroller 16 inserts a selected channel at the bottom of the list 81. In this manner, the user can select or delete channels from the viewer preference list in any desired order.

The available channel list 80 may also be provided with categorical entries 83, such as movies, news, sports or children's shows. The user may also highlight any of these entries and put them into the viewer preference list 81. If the user does include a category in his viewer preference list 81, when the user issues channel up or down commands, the system will display, in sequence, first the user's selected preferred channels in numerical order and then all channels having a program whose content corresponds to the selected category or categories at the time.

Once the user has revised the channel preference list 81 in the described manner, the microcontroller 16 will follow the stored user-specified channel sequence in response to a change-channel command made by the user employing one of the direction arrow keys. To activate the viewer prefer-

ence list, the user depresses one of the three check-mark icon keys 48A, 48B or 48C on the top of the remote controller shown in FIG. 4. The viewer preference list can be used to selectively limit tuning of the television receiver or display of schedule information in any of the operating modes of the electronic program guide. In the present embodiment, once a preference list is activated, the system will limit the tuning of the television receiver and the display of schedule information in the FLIP, and BROWSE modes, as well as in the grid category and channel listings in the MENU mode, only to those channels designated in the activated viewer preference list. The tuner can not be tuned to, and no corresponding schedule information can be displayed for, any channel not entered in the viewer preference list when it is activated. In this regard, it should be noted that setting a key lock access in the Parental Guidance 301, MPAA 308 or Channel Block 303 categories produces a different result than when using other display criteria, such as the Channel Preference List of preferred channels discussed above. Thus, while a key lock access will prevent audio and video program information, but not schedule information, from being displayed or ordered absent entry of an authorization code, if a particular channel is included in the Channel Preference list and also has a key lock access activated in the Channel Block category 303 of the Key Lock Access mode, that channel or its corresponding schedule information will not be displayed at any time.

To deactivate a previously selected viewer preference list, the user toggles the appropriate check-mark icon key on the remote controller 40 of FIG. 4. Once deactivated, the system defaults to displaying and tuning all available channels, as well as displaying schedule information for all available channels.

Alternatively, the viewer preference list 81, if activated, can be used to control tuning and display of schedule information only in selected modes, such as only in the FLIP mode, thus allowing the user to tune and view corresponding schedule information only for those channels entered in the preference list 81 in the FLIP mode, while viewing all channels and corresponding schedule information in all other modes.

In this latter configuration, as well as in the instance where no channel preference list is activated and the system is in default mode, if a channel appears in the viewer preference list 81 that corresponds to a service not subscribed to by the user, the microcontroller 16 causes an ordering submenu to appear instead of displaying a program signal along with the graphic overlay, as shown in FIG. 9. This submenu indicates to the user that he does not currently subscribe to the selected service, and then asks the user if he would like to order the service. If the user responds affirmatively, the program schedule system takes the user to another ordering submenu to confirm the user's request, as with impulse ordering.

The program guide also may be configured with a Locator screen 201, as shown in FIG. 37, which aids the viewer in channel selection and definition of a favorite channel list. The Locator screen 201 displays all available channel numbers grouped according to the source of the program information appearing on any particular channel at any particular time, e.g., broadcast, cablecast, pay-per-view, near video on demand, satellite, or other source of program material. Thus, the Locator screen 101 can be used to locate any particular channel or service because the groupings provide a quick and efficient method for scrolling through the list of available channels. The channel numbers also may be grouped according to other criteria, such as program category, pro-

gram content, program rating or other content-based standard, time of availability, numerical order, or other logical grouping.

In the example shown in FIG. 37, the user navigates within the Locator screen 201 using the direction keys 43A and 43B on the remote controller 40. The right and left direction keys 43B move the selection cursor within the category rows, while the up and down direction keys 43A are used to select a particular category. From the Locator screen 201, any particular channel can be selected for viewing by positioning the selection cursor on the desired channel and depressing either the enter key 44 or an optional tune key (not shown) on the remote controller 40.

In addition to aiding in channel selection, the Locator screen 201 also provides the user with the ability to conveniently define favorite channel lists. To do so, the user first moves the selection cursor to the desired channel by using the direction keys 43A and 43B or numeric digit keys 42 on the remote controller 40, and then depresses a favorite channel key 46A provided on the remote controller 40, which causes the display to change in some manner or characteristic as an indication that the channel has been selected as a favorite channel, such as by changing the color of the channel identification text or the text background, by displaying an appropriate icon or by some other appropriate identification scheme. In the remote controller 40 shown in FIG. 4, the pound key “#” can function as the favorite channel key.

Also, if multiple favorite channel lists are being used, the user would depress the appropriate favorite channel key on the remote controller to select a particular list before depressing the favorite channel key. For example, as discussed above, the remote controller 40 shown in FIG. 4, has three color-coded check-mark favorite channel keys 48A, 48B and 48C, which provide for at least three individual favorite channel lists for three individual users. Different identification characteristics could be displayed on the Locator screen 201 to indicate that a particular favorite channel list is selected. For example, the icon or image used to enable a favorite channel list on the remote controller, such as the check mark key 48A used on the remote controller 40 shown in FIG. 4, could be displayed on the Locator screen 201, as well as other screens of the program guide, when a favorite channel list is enabled. Alternatively, the color of the displayed text or background could be changed to match the color of the selected favorite channel key.

The Locator screen 201 may be accessed via several paths. For example, it may be included as a virtual channel that is conveniently positioned in the channel-tuning sequence, such as between the highest and lowest available channel numbers—for example, a virtual channel 0. To the user, such a virtual channel appears to be a conventional channel. However, it requires no additional bandwidth as a carrier. For example, it can be digitally produced at the subscriber station or included in an appropriate blanking interval in existing bandwidth frequencies. In this manner, the virtual channel is accessible either by entering the corresponding channel number using the numeric digit keys 42 on the remote controller, or by using the up and down direction keys 43A to wrap around from the highest to the lowest channel number, or vice versa. As shown in FIG. 38, it also may be desirable to provide a suitable identifier, such as an icon or text message 210, in the MAIN MENU display 215, from which the user could access the Locator screen 201 simply by highlighting the identifier 210 with the selection cursor and depressing the enter key 44 on the remote controller 40. Alternatively, the remote controller

may be provided with a key corresponding to the Locator screen 201 which would cause the microcontroller to display the Locator screen 201 when the user depressed it.

In addition to Channel Preference or Favorite Channel keys, the remote controller 40 can also be supplied with a number of user-activated category preference icon keys, e.g., movies, sports, or children's programming. The system can be adapted to present to the user only those programs meeting particular preference category when it is activated by the user. As with the Channel Preference icons, the microcontroller may display the icon corresponding to the activated preference category to remind the user of the currently activated mode of system operation.

The question mark icon 162 at the far right of the third horizontal bar in the menu of FIG. 16 identifies a program guide system "Help" mode in which information explaining the operation of the system is displayed for the user. Again, by manipulating the cursor using the appropriate keys on the remote controller, the user can select this mode. Once selected, the next submenu appearing in the Help mode asks the user to identify the particular portion of the system about which the user would like to view Help information.

The icons appearing in the last horizontal bar of the MENU mode identify certain interactive and/or other types of information services which the programming system, acting as a gateway, makes available to the user as shown in FIG. 17. By manipulating the cursor, the user can select any one of the identified services, as shown in FIGS. 31-35.

For example, if the user initially selects the "X*PRESS" icon appearing in the last horizontal bar, he is presented with a submenu such as that shown in FIG. 31. Using the direction arrow and enter keys on the remote controller, the user selects one of the three entries appearing in the display of FIG. 31. Once a particular entry is selected, the electronic program guide connects the user to the selected service and passes control to the particular service application software, as shown in FIGS. 32-35.

Alternatively, the remote controller 40 can be supplied with a plurality of content-specific keys corresponding to a plurality of content-specific categories of programming, e.g., a Sports key, News key, Movie key, etc. When the user depresses a content-specific key, a content-specific mode is initiated. In FIG. 4, the remote controller is equipped with a Sports key 49. If the user depresses the Sports key 49, the microcontroller will limit the display of programs and/or program schedule information to those that are sports-related. The microcontroller will block all other programming or schedule information from appearing on the television receiver. The microcontroller can be adapted to distinguish programs and schedule information that are sports-related by examining an appropriate code associated with the program or schedule information.

As discussed above, coding can be accomplished using any number of methods, such as by including an appropriate code in the vertical blanking interval of the program signal, or in an appropriate memory location in the database record of the program schedule information, or if the schedule information is being received on a broadband network, by including it in an appropriate blanking interval. The user activates a content-specific mode by depressing the appropriate content-specific key in any mode of operation of the electronic programming guide, including the aforescribed FLIP, BROWSE or MAIN MENU modes, as well as when no schedule information is being displayed and only a program signal is visible on the television receiver. Once a content-specific mode is requested by the user, the micro-

controller immediately and directly enables the content-specific programming criteria, and maintains it for all operating modes of the guide until disabled, which can be accomplished, for example, by toggling the Sports key 49.

Instead of a dedicated content-specific key, such as Sports key 49, the system may be configured with a single, generic content-specific key, which, when activated, would cause the microcontroller to display a content-specific menu containing a list of all content-specific categories available to the user. The user then could highlight a particular category by manipulating the selection cursor using the direction arrow keys on the remote controller and select it by depressing the ENTER or OK key 44. As an alternative to using a content-specific key on the remote controller, access to the content-specific menu can be effected by providing an appropriate identifier in another menu screen of the electronic guide, such as in the LOCATOR, SETUP or MAIN MENU screens.

In addition to blocking all non-selected content-specific programming when a particular content-specific category has been selected, the microcontroller can be programmed to enable all added-value programming or services that are specially related to the selected content-specific category. For example, if the user activates a Sports content-specific mode, the microcontroller, in addition to allowing only sports programming or schedule information related to sports programming to be displayed, will proactively seek out and enable all sports related added-value services, such as related trivia or video games, up-to-date scores while a game is in progress, team schedules, replays of prior games of the selected teams or players, ticket or souvenir purchasing, etc. Thus, the information available from the programming or service can be integrated into the environment of the electronic program guide. Rather than simply passing control to another service as described above, in this manner the electronic program guide would function as a system integrator or interface to combine the available added-value information into a package within the electronic guide environment, thus essentially creating a series of modular electronic program applications corresponding to a variety of available content-specific categories.

The Setup screen shown in FIG. 40 also includes a Text Location category 275, which contains the textual entries "Bottom of Screen" and "Top of Screen." By navigating to the Text Location category 275 using the up and down direction keys 43A on the remote controller 40, and to either the "Top" or "Bottom" entries in that category using the left and right direction keys 43B on the remote controller, and then depressing the enter or select key 44, the user can control the position of the overlay windows used to display information in various operating modes of the electronic program guide. The Setup screen of FIG. 40 provides the user with two positional choices: the top or bottom of the screen. Depending on the modes of operation of the program guide, it may be desirable to provide the user with more positional choices in viewing area of the television receiver, or to provide the user with the ability to choose a different position for information displayed different operating modes.

The operation of the "By Title" display option will now be described. This option permits users to display program titles alphabetically by title. In addition, the user may input a string of characters representative of a program title or beginning portion thereof and search the program listings for the desired title. This permits a user to locate a program, series, movie, or event without knowing either the channel or time for the program.

One embodiment of the "By Title" option operates as follows. When the user selects the "By Title" box 321 shown in FIG. 38C, she is presented with the screen shown in FIG. 38D.

As shown in FIG. 38D, the system is configured to automatically display the listings in alphabetical order. It is preferable that upon entering the "By Title" option, the first displayed set of listings correspond to the beginning of the alphabet. However, it may also be configured such that if the user previously invoked the "By Title" option and then exited it, the listings will begin at the point where the user last reviewed listings using this option. The display line 325 for each listing preferably includes the program, movie, or series title, network, channel, day (today or tomorrow), and time. For some programs, such as movies and sporting events, additional descriptive information may be included. In addition, display lines may include the "I" icon to indicate that additional information about the program is available and/or other icons conveying other kinds of information or advisories. Color coding may be used to distinguish different program types. For example, movies may all be displayed in one background color while sports programs utilize a different color.

In systems having a large database of program schedule information, e.g., one with a large number of channels and/or listings for many days of programming, it may be desirable to utilize only a subset of the total listings database for display in the "By Title" mode to reduce the time required to search the listings. For example, in the particular embodiment shown in FIG. 38D, only programs scheduled for the present day or the following day are displayed. Additionally, it may be desirable to exclude uninformative listings identified only by generic titles such as "News," "Infomercial," "Music Video," and "To Be Announced."

The "By Title" option operates in two different modes, search and scroll. In the scroll mode of operation shown in FIG. 38E, the user may manually scroll through the alphabetical list of program titles using the up/down arrow keys 43A on the remote control unit 40. In FIG. 38E, the program "Mad About You" is highlighted indicating the cursor is placed on this program listing. The character boxes 330 in FIG. 38E do not control the listings display in this mode, as the display is controlled with the up/down keys. The "t" icon 335 in the display line indicates that a reminder message has been set for this program as discussed above. The envelope icon in the upper right hand corner of the display indicates to the user that there are messages in the message center. These messages may originate from and relate to the cable system, as discussed above. The scroll mode is accessed by depressing the ENTER or "OK" key 44 on the remote control upon initiation of the "By Title" option or at any later point when the search mode is activated.

The second mode of operation of the "By Title" option is search mode. In the preferred embodiment, search mode is the default mode activated upon selection of the "By Title" option. Search mode may also be accessed by depressing either the left or right arrow keys when in scroll mode. In search mode, the user may input one, two, three, or four characters of a program title using the character boxes 330 shown in FIG. 38F. Characters are input using the up/down arrow keys 43A and the ENTER or "OK" key 44. By depressing the up/down keys, the characters in the character boxes cycle through the letters of the alphabet and the digits 0-9. The arrows displayed around the perimeter of a character box designate the box currently activated and the keys which may be depressed. Once the desired character is selected, depressing the right arrow key moves the cursor to the second character box and so forth.

In the embodiment disclosed in FIG. 38F, when the cursor is moved to an adjacent character box, the system automatically searches the listings and displays the appropriate listings, with the listing closest to the entered character or characters highlighted. Alternatively, the system may be configured to search in real time as characters are changed in the character boxes. In FIG. 38F, the characters "M," "A," and "D" have been selected in the boxes in order to search for the program "Mad About You." In the listings portion of the screen, the display line listing "Mad About You" is displayed in the first line, indicating that this program is the closest match to the characters entered. The user may also input numbers in the character boxes so that programs with numbers in the beginning of the title may be searched (i.e., the movie "2001"). To return to scroll mode the "OK" or "ENTER" key 44 is depressed.

Those of skill in the art will recognize that there are many possible variations to the embodiment of the "By Title" option depicted in FIGS. 38C-38F. For example, the user may be given control over the particular subset of listings to display. Thus, the listings may be limited to today's programs or expanded to a full week of programs. In addition, a greater or lesser number of character boxes may be used. Additionally, the program listings may be limited to channels previously selected in a Favorite Channel list. Alternatively, the "By Title" option may be combined with one of the other operating modes of the system. For example, the system may be readily configured to limit the "By Title" listings display to a single channel, time or theme.

One of the novel features of the disclosed invention is the textfit system. The preferred embodiment of the text fit system includes an interactive computer program used to edit the program listings data before it is transmitted to the user and stored in memory. The interactive system operates as follows: unedited (or partially edited) program listings information is loaded into data a processor. The data includes program titles, program schedule times, duration, category, as well as additional descriptive information dependent on the type of program. For example, for movies the data includes the MPAA rating, year of the movie, whether it is in black and white, and a list of starring actors and actresses.

The data processor extracts only the program title data which includes television program titles as well as movie titles, sporting events and titles for other special events. Based on the duration of the program, the data processor first analyzes the listings data to determine what grid size listings are needed for each title. Thus, a two hour movie could require four different edited titles to fit into each of the four different size grid cells (30, 60, 90, 120 minutes). The data processor then determines how much space is required to display the title based on its character length. If the title is to be displayed in the program schedule grid using a proportional font and character to character kerning, the data processor may also account for these factors in determining the space required to display a title. The determination would then be based on the number of pixels required for the particular combination of characters in the title. The amount of space available for display of a title depends on the size of the grid cell and the space required for display of icons, when activated.

If the data processor determines that a full title requires too much space to fit into one or more grid cells, the title is then presented to the editor using a suitable display device connected to the data processor, such as a CRT. The editor is then queried to alter the title so that it will fit in the allotted space. If the title must be edited for more than one cell size,

the editor is queried to edit each of these separately. In the preferred embodiment of the interactive program, the editor is shown in real time whether the edited title will fit in the designated grid cell.

In the preferred embodiment, two lines of text are displayed in each grid cell of the program listings. The title, as edited, appears on the first line, and if necessary, continues onto the second line. The decision to wrap-around to the second line is based on whether natural breaks exist in the title such as spaces between words, commas, periods, hyphens, etc. These are standard techniques used in word processing software routines. The editor may also be queried to edit a title in the situation where the full title will fit on the allotted two lines, but a hyphen is required because there are no natural breaks in the title.

Prior to querying the editor to shorten a title, the data processor compares the title with a stored library of shortened titles to determine if the title had previously been shortened while editing another listings database. Each time changes are made by the editor to a title, the shortened title is added to the library. It is apparent that this process of building a library of shortened titles greatly reduces the manual input required.

A flow chart illustrating the process by which the text fit system operates is shown in FIG. 42. The chart illustrates the operation of editing a listing for display in a program grid for a single platform, but operation is the same for all platforms.

Text editing may be necessary in other situations besides that where multiple size grid cells are used for display of the same title. For example, the disclosed program guide may run on several different platforms, with each one having different constraints and grid cell space availability. Some may not display the text in proportional fonts and some may have other limitations reducing the available space. Thus, in the preferred embodiment the interactive program would request edits for all platforms for which they required at the same time. In addition, editing of text may be required for display modes other than a grid of program listings. For example, in the "Listings by Channel" display of FIG. 20, programs are listed on an entire, fixed-length line, but the length of the line may vary from platform to platform, so that the text fit system may be employed for the purpose of editing listings for the different platforms in this display mode as well. The space available for the display of text will also depend on how much space is reserved for icon display. The same process as that shown in FIG. 42 would apply, except that there would be no need to determine what grid sizes are needed because a fixed length line is used for display rather than multiple sized grid cells.

It will be apparent to those of skill in the art that the disclosed text fit system has applications beyond that of title editing alone. The system may be easily modified to provide editing of messages, "I" screen storylines, pay-per-view promotional copy, and similar text messages so that they will fit into the designated space available for display of the text. In fact, the system may be used to edit any text for display in the disclosed program schedule system.

The computer program for the microcontroller 16 may also include a schedule for the display of varying background views upon which the program schedule information is overlaid either partially or in a full screen display. The background views may be stored as bit maps in memory or in another storage medium, such as an optical storage device. For example, the microcontroller 16 may be programmed to issue a command to the VDG every morning at 6:00 AM to display a sunrise in the background. The

background may then be changed accordingly throughout the day to, for example, a blue sky or a nighttime view. It also may vary, e.g., by time of day, day of week, month, year or season. The mood background also could change depending on the particular category of programming that the user is watching or to which selected schedule information pertains. The mood background also may be adapted to display scenes that reflect the particular viewing area in which the user is situated, like the Rocky Mountains, or Mr. Rainier, etc. It also may be possible to display standard scenes, such as an ocean or forest scene. Moreover, the audio background also could be adjusted to relate to the particular mood background then being displayed. In addition, different background views may be used for holidays and special events, such as Christmas, Fourth of July, Superbowl Sunday, etc. The purpose of the background views is to help ease the monotony of viewing program listings. The microcontroller 16 could be adapted automatically to coordinate the display of the mood background. The user also could be given the ability to choose from among various mood background displays by adapting the microcontroller to display an appropriate mood option menu that lists the mood background options available to the user and allows the user to select one or more by manipulating the selection cursor. Access to such a mood option menu could be achieved by supplying an appropriate identifier, textual or visual, in an appropriate menu of the system, such as the LOCATOR or SETUP screen.

Additionally, the electronic program guide could be configured to store a unique digital identifier for each program along with its schedule information and later use the identifier—e.g., by transmitting it—to indicate to a recording or storage device, such as a video recorder, that the user wishes to record the program. The program guide could also use the identifier to automatically control operation of the video recorder. The electronic program guide could also be configured to use other stored schedule information for this purpose.

The form and content of a particular computer program to implement the invention disclosed herein will be readily apparent to those skilled in the art of video system programming and graphic display. A flow chart showing the operation logic of the system is shown in FIG. 36. It will also be appreciated by those skilled in the art that there can be departure from the specific embodiment of the invention described herein without departing from the true scope of the claims appended hereto.

We claim:

1. An electronic television programming guide for use in connection with a television receiver for displaying a plurality of television programs from a plurality of program sources on a plurality of user-selectable television channels comprising:

user control means for issuing control commands, including channel-control commands;
data processing means for receiving said control commands and for generating video control commands;
video display generator means adapted to receive video control commands from said data processing means for generating and displaying a visual display of a plurality of television program titles on said television receiver, said plurality of television program titles arranged alphabetically by title; and

selection means for allowing said user to select a title for display on said television receiver by selecting the first n characters of said title, where n is greater than one;

said data processing means being responsive to said selection means and adapted to select said plurality of television program titles for display on said television receiver in response to said n characters;

wherein said video display generator means displays said n characters and said selection means comprises means for causing each of said n characters to cycle forward and backward through a plurality of alphanumeric characters and means for assigning one of said alphanumeric characters to each of said n characters.

2. The electronic television programming guide of claim 1 wherein said video display generator means changes said display of television program titles substantially immediately after selection of each of said n characters.

3. The electronic television programming guide of claim 1 wherein said video display generator means displays said n characters concurrently with said plurality of program titles.

4. The electronic television programming guide of claim 1 wherein said video display generator means comprises cursor means for designating one of said displayed titles in further response to said n characters.

5. The electronic television programming guide of claim 4 wherein said user selection means further comprises means for selecting said designated program for viewing.

6. The electronic television programming guide of claim 1 wherein said video display generator means changes said display of television program titles as said selection means cycles through said plurality of alphanumeric characters.

7. The electronic television programming guide of claim 1 wherein said visual display comprises channel, day, and time information for said program titles.

8. The electronic television programming guide of claim 1 wherein said selection means comprises means for causing a cursor to scroll through said displayed titles.

9. The electronic television programming guide of claim 1 wherein said display of television program titles consists of titles for programs scheduled for display on the same channel.

10. The electronic television programming guide of claim 1 wherein said display of television program titles consists of titles for programs scheduled for display on the same day and at the same time.

11. The electronic television programming guide of claim 1 wherein said display of television program titles consists of titles for programs scheduled for display on a plurality of user-defined favorite channels comprising a subset of said plurality of user-selectable television channels.

12. In an electronic television programming guide for use in connection with a television receiver for displaying a plurality of television programs from a plurality of program sources on a plurality of user-selectable television channels comprising, a method for selecting a program for display on said receiver by searching a database of program schedule information alphabetically by title, said method comprising: generating user control commands with a user control means;

selecting and displaying the first n characters of a program title with said user control means, where n is greater than one, wherein each said character is selected from a plurality of alphanumeric characters by cycling forward and/or backward through said alphanumeric characters and assigning one of said alphanumeric characters to each of said n characters;

receiving said user control commands and searching a database of program schedule information in response to said n characters; and

generating and displaying a visual display of television program titles displayed alphabetically by title in response to said searching of said database.

13. The method of claim 12 further comprising changing said visual display of television program titles substantially immediately upon selection of each of said n characters.

14. The method of claim 12 wherein said n characters are displayed concurrently with said visual display of program titles.

15. The method of claim 12 comprising designating one of said displayed titles in further response to said searching of said database.

16. The method of claim 15 further comprising selecting said designated program for viewing.

17. The method of claim 12 wherein said display of television program titles is changed as one of the n characters is changed.

18. The method of claim 12 comprising displaying channel, day, and time information for said program titles.

19. The method of claim 12 further comprising scrolling through said displayed titles using said user control means.

20. The method of claim 12 wherein said display of television program titles consists of titles for programs scheduled for display on the same channel.

21. The method of claim 12 wherein said display of television program titles consists of titles for programs scheduled for display on the same day and at the same time.

22. The method of claim 12 wherein said display of television program titles consists of titles for programs scheduled for display on a plurality of user-defined favorite channels comprising a subset of said plurality of user-selectable television channels.

23. In an electronic television programming guide for use in connection with a television receiver, a method for selecting program schedule information for display on said receiver by selecting a plurality of characters in a desired title for one of said programs, the method comprising:

a) providing a user control means including up/down arrow keys;

b) displaying a plurality of n character display cells on said television receiver, where n is greater than 1;

c) displaying an alphanumeric character in the first said display cell in response to a first user control command generated by said user control means;

d) changing said displayed alphanumeric character in response to depression of one of said up/down arrow keys on said user control means if said displayed alphanumeric character is not the correct first character for said desired title;

e) selecting said displayed alphanumeric character as said first character of said desired title in response to a second user control command;

f) displaying a plurality of program titles alphabetically in response to said first selected alphanumeric character;

g) repeating steps c), d), and e) for the second character of said desired title and displaying a plurality of program titles alphabetically in response to said first and second selected alphanumeric characters of said desired title; and

h) repeating steps c), d), and e) for the third character of said desired title and displaying a plurality of program titles alphabetically in response to said first, second and third selected alphanumeric characters of said desired title if said desired title is not displayed following step g).

EXHIBIT

**FINAL OFFICE ACTION
MAILED DECEMBER 10, 2007**



UNITED STATES PATENT AND TRADEMARK OFFICE

UNITED STATES DEPARTMENT OF COMMERCE
United States Patent and Trademark Office
Address: COMMISSIONER FOR PATENTS
P.O. Box 1450
Alexandria, Virginia 22313-1450
www.uspto.gov

APPLICATION NO.	FILING DATE	FIRST NAMED INVENTOR	ATTORNEY DOCKET NO.	CONFIRMATION NO.
09/313,532	05/13/1999	ROGER YOUMAN		4047

1473 7590 12/10/2007
ROPES & GRAY LLP
PATENT DOCKETING 39/361
1211 AVENUE OF THE AMERICAS
NEW YORK, NY 10036-8704

EXAMINER

USTARIS, JOSEPH G

ART UNIT	PAPER NUMBER
----------	--------------

2623

MAIL DATE	DELIVERY MODE
-----------	---------------

12/10/2007

PAPER

Please find below and/or attached an Office communication concerning this application or proceeding.

The time period for reply, if any, is set in the attached communication.

Office Action Summary

Application No.

09/313.532

Applicant(s)

YOUAMAN ET AL.

Examiner

Joseph G. Ustaris

Art Unit

2623

-- The MAILING DATE of this communication appears on the cover sheet with the correspondence address --
Period for Reply

A SHORTENED STATUTORY PERIOD FOR REPLY IS SET TO EXPIRE 3 MONTH(S) OR THIRTY (30) DAYS, WHICHEVER IS LONGER, FROM THE MAILING DATE OF THIS COMMUNICATION.

- Extensions of time may be available under the provisions of 37 CFR 1.136(a). In no event, however, may a reply be timely filed after SIX (6) MONTHS from the mailing date of this communication.
- If NO period for reply is specified above, the maximum statutory period will apply and will expire SIX (6) MONTHS from the mailing date of this communication.
- Failure to reply within the set or extended period for reply will, by statute, cause the application to become ABANDONED (35 U.S.C. § 133). Any reply received by the Office later than three months after the mailing date of this communication, even if timely filed, may reduce any earned patent term adjustment. See 37 CFR 1.704(b).

Status

- 1) ☒ Responsive to communication(s) filed on 16 November 2007.
- 2a) ☒ This action is FINAL. 2b) ☐ This action is non-final.
- 3) ☐ Since this application is in condition for allowance except for formal matters, prosecution as to the merits is closed in accordance with the practice under *Ex parte Quayle*, 1935 C.D. 11, 453 O.G. 213.

Disposition of Claims

- 4) ☒ Claim(s) 1-55 is/are pending in the application.
- 4a) Of the above claim(s) _____ is/are withdrawn from consideration.
- 5) ☒ Claim(s) 1-23 is/are allowed.
- 6) ☒ Claim(s) 24-55 is/are rejected.
- 7) ☐ Claim(s) _____ is/are objected to.
- 8) ☐ Claim(s) _____ are subject to restriction and/or election requirement.

Application Papers

- 9) ☐ The specification is objected to by the Examiner.
- 10) ☐ The drawing(s) filed on _____ is/are: a) ☐ accepted or b) ☐ objected to by the Examiner.
Applicant may not request that any objection to the drawing(s) be held in abeyance. See 37 CFR 1.85(a).
Replacement drawing sheet(s) including the correction is required if the drawing(s) is objected to. See 37 CFR 1.121(d).
- 11) ☐ The oath or declaration is objected to by the Examiner. Note the attached Office Action or form PTO-152.

Priority under 35 U.S.C. § 119

- 12) ☐ Acknowledgment is made of a claim for foreign priority under 35 U.S.C. § 119(a)-(d) or (f).
- a) ☐ All b) ☐ Some * c) ☐ None of:
- ☐ Certified copies of the priority documents have been received.
 - ☐ Certified copies of the priority documents have been received in Application No. _____.
 - ☐ Copies of the certified copies of the priority documents have been received in this National Stage application from the International Bureau (PCT Rule 17.2(a)).

* See the attached detailed Office action for a list of the certified copies not received.

Attachment(s)

- 1) ☐ Notice of References Cited (PTO-892)
- 2) ☐ Notice of Draftsperson's Patent Drawing Review (PTO-948)
- 3) ☐ Information Disclosure Statement(s) (PTO/SB/08)
Paper No(s)/Mail Date _____
- 4) ☐ Interview Summary (PTO-413)
Paper No(s)/Mail Date _____
- 5) ☐ Notice of Informal Patent Application
- 6) ☐ Other: _____

DETAILED ACTION

Response to Amendment

1. This action is in response to the amendment dated November 16, 2007 in application 09/313,532.

Reissue Applications

2. Claims 24-55 are rejected under 35 U.S.C. 251 as being an improper recapture of broadened claimed subject matter surrendered in the application for the patent upon which the present reissue is based. See *Pannu v. Storz Instruments Inc.*, 258 F.3d 1366, 59 USPQ2d 1597 (Fed. Cir. 2001); *Hester Industries, Inc. v. Stein, Inc.*, 142 F.3d 1472, 46 USPQ2d 1641 (Fed. Cir. 1998); *In re Clement*, 131 F.3d 1464, 45 USPQ2d 1161 (Fed. Cir. 1997); *Ball Corp. v. United States*, 729 F.2d 1429, 1436, 221 USPQ 289, 295 (Fed. Cir. 1984). A broadening aspect is present in the reissue which was not present in the application for patent. The record of the application for the patent shows that the broadening aspect (in the reissue) relates to claim subject matter that applicant previously surrendered during the prosecution of the application. Accordingly, the narrow scope of the claims in the patent was not an error within the meaning of 35 U.S.C. 251, and the broader scope of claim subject matter surrendered in the application for the patent cannot be recaptured by the filing of the present reissue application.

Regarding claims 24 and 40, in the parent application 08/346,603, applicant surrendered a broad claim 1 in view of an amended version in amendment 'A', dated

March 07, 1996. Amendment 'A' specifically presents a claim which included the limitation "...wherein said video display generator display said n characters and said selection means comprises means for causing said character displays to cycle forward and backward through a plurality of alphanumeric characters and means for assigning one of said alphanumeric characters to each of said n characters."

On page 14 of the amendment 'A', applicant specifically argues, "Furthermore, even if the teachings of Reed are applied to either Young or Vogel, because Reed does not disclose how to select multiple characters in a title using only a remote control device, one of ordinary skill in the art would still not be possessed of the invention described and claimed by applicants. For example, parent application 08/346,603, claim 1 has been amended to recite i) that a plurality of characters in the title are input by the user, and ii) the specific means by which this is done - providing a user selection means 'to cycle forward and backward through a plurality of alphanumeric characters' in order to locate each of the desired characters in the title."

At least the argued limitation of "cycle forward and backward through a plurality of alphanumeric characters" in claim 1 of the parent application 08/346,603 appears to be absent from the reissue application claims 24 and 40. There doesn't appear to be a broader version of this argued limitation on the reissue application claims 24 and 40 in order to avoid recapture under Ex parte Eggert, see MPEP 1412.02.

Allowable Subject Matter

3. Claims 1-23 are allowed.

Response to Arguments

4. The rejection under 37 C.F.R. 3.73(b) is now withdrawn in view of the new statement of consent.

Applicant's arguments filed November 16, 2007 have been fully considered but they are not persuasive.

Applicant also argues that claims 24 and 40 include broader limitation that describes the specific means used by which the selection means operates to select the n characters used to search for a title. However, upon further review with Chris Kelley and Ken Wieder, it was determined that there doesn't appear to be a broader version of "cycle forward and backward through a plurality of alphanumeric characters" on the reissue application claims 24 and 40 in order to avoid recapture under Ex parte Eggert as discussed above. In the parent application 08/346,603, applicant has amended and argued this limitation in order to overcome the prior art (See discussion above).

The examiner suggests amending the claims 24 and 40 to incorporate the cycling features in order to avoid recapture under Ex parte Eggert.

Conclusion

5. Applicant's amendment necessitated the new ground(s) of rejection presented in this Office action. Accordingly, **THIS ACTION IS MADE FINAL**. See MPEP § 706.07(a). Applicant is reminded of the extension of time policy as set forth in 37 CFR 1.136(a).

Art Unit: 2623

A shortened statutory period for reply to this final action is set to expire THREE MONTHS from the mailing date of this action. In the event a first reply is filed within TWO MONTHS of the mailing date of this final action and the advisory action is not mailed until after the end of the THREE-MONTH shortened statutory period, then the shortened statutory period will expire on the date the advisory action is mailed, and any extension fee pursuant to 37 CFR 1.136(a) will be calculated from the mailing date of the advisory action. In no event, however, will the statutory period for reply expire later than SIX MONTHS from the date of this final action.


Any inquiry concerning this communication or earlier communications from the examiner should be directed to Joseph G. Ustaris whose telephone number is 571-272-7383. The examiner can normally be reached on M-F 7:30-5 PM; Alternate Fridays off.

If attempts to reach the examiner by telephone are unsuccessful, the examiner's supervisor, Christopher S. Kelley can be reached on 571-272-7331. The fax phone number for the organization where this application or proceeding is assigned is 571-273-8300.

Art Unit: 2623

Information regarding the status of an application may be obtained from the Patent Application Information Retrieval (PAIR) system. Status information for published applications may be obtained from either Private PAIR or Public PAIR. Status information for unpublished applications is available through Private PAIR only. For more information about the PAIR system, see <http://pair-direct.uspto.gov>. Should you have questions on access to the Private PAIR system, contact the Electronic Business Center (EBC) at 866-217-9197 (toll-free). If you would like assistance from a USPTO Customer Service Representative or access to the automated information system, call 800-786-9199 (IN USA OR CANADA) or 571-272-1000.


JGU
December 4, 2007


CHRIS KELLEY
SUPERVISORY PATENT EXAMINER
TECHNOLOGY CENTER 2600

EXHIBIT

AMENDMENT A FILED MARCH 7, 1996

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re application of: Youman et al.

Serial No.: 08/346,603

Group No.: 2602

Filed: Nov. 29, 1994

Examiner: Grant

For: Electronic Television Program Guide Schedule System and Method with Display and Search of Program Listings by Title

AMENDMENT AND RESPONSE TO OFFICE ACTION

Hon. Commissioner of Patent and Trademarks
Washington, D.C. 20231

Sir:

In response to the office action dated January 30, 1996, please amend
the application as follows:

In the claims:

Sub 1
1.(amended) An electronic television programming guide for use in
connection with a television receiver for displaying a plurality of television programs
from a plurality of program sources on a plurality of user-selectable television
channels comprising:
user control means for issuing control commands, including
channel-control commands;

AI
Cont

data processing means for receiving said control commands and for generating video control commands;

a video display generator adapted to receive video control commands from said data processing means for generating and displaying a visual display of a plurality of television program titles on said television receiver, said plurality of television programs displayed alphabetically by title; and

selection means for allowing said user to select a title for display on said television receiver by selecting the first n characters of said title, where n is greater than [or equal to] one; said data processing means being responsive to said selection means and adapted to select said plurality of television program titles for display on said television receiver in response to said n characters;

wherein said video display generator displays said n characters and said selection means comprises means for causing said character displays to cycle forward and backward through a plurality of alphanumeric characters and means for assigning one of said alphanumeric characters to each of said n characters.

Please add the following claims:

Sub B3

2. The electronic television programming guide of claim 1 wherein said video display generator changes said display of television program titles substantially immediately after selection of each of said n characters.

3. The electronic television programming guide of claim 1 wherein said video display generator displays said n characters concurrently with said plurality of program titles.

4. The electronic television programming guide of claim 1 wherein said video display generator comprises cursor means for designating one of said displayed titles in further response to said n characters.

5. The electronic television programming guide of claim 4 wherein said user selection means further comprises means for selecting said designated program for viewing.

Sub B3

6. The electronic television programming guide of claim 1 wherein said video display generator changes said display of television program titles as said video display generator cycles through said plurality of alphanumeric characters.

7. The electronic television programming guide of claim 1 wherein said visual display comprises channel, day, and time information for said program titles.

8. The electronic television programming guide of claim 1 wherein said selection means comprises means for causing a cursor to scroll through said displayed titles.

9. The electronic television programming guide of claim 1 wherein said display of television program titles consists of titles for programs scheduled for display on the same channel.

10. The electronic television programming guide of claim 1 wherein said display of television program titles consists of titles for programs scheduled for display on the same day and at the same time.

11. The electronic television programming guide of claim 1 wherein said display of television program titles consists of titles for programs scheduled for display on a plurality of user-defined favorite channels comprising a subset of said plurality of user-selectable television channels.

Sub BT 12. In an electronic television programming guide for use in connection with a television receiver for displaying a plurality of television programs from a plurality of program sources on a plurality of user-selectable television channels comprising, a method for selecting a program for display on said receiver by searching a database of program schedule information alphabetically by title, said method comprising:

AS
cont

generating user control commands with a user control means;
selecting and displaying the first n characters of a program title with
said user control means, where n is greater than one, wherein each said
character is selected from a plurality of alphanumeric characters by cycling
said character displays forward and/or backward through said alphanumeric
characters and assigning one of said alphanumeric characters to each of said n
characters;

receiving said user control commands and searching a database of
program schedule information in response to said n characters; and

generating and displaying a visual display of television program titles
displayed alphabetically by title in response to said searching of said database.

13. The method of claim 12 further comprising changing said visual
display of television program titles substantially immediately upon selection of each of
said n characters.

14. The method of claim 12 wherein said n characters are displayed
concurrently with said visual display of program titles.

15. The method of claim 12 comprising designating one of said
displayed titles in further response to said searching of said database.

16. The method of claim 15 further comprising selecting said designated program for viewing.

17. The method of claim 12 wherein said display of television program titles is changed as one of the n characters is changed.

18. The method of claim 12 comprising displaying channel, day, and time information for said program titles.

19. The method of claim 12 further comprising scrolling through said displayed titles using said user control means.

20. The method of claim 12 wherein said display of television program titles consists of titles for programs scheduled for display on the same channel.

21. The method of claim 12 wherein said display of television program titles consists of titles for programs scheduled for display on the same day and at the same time.

22. The method of claim 12 wherein said display of television program titles consists of titles for programs scheduled for display on a plurality of user-defined favorite channels comprising a subset of said plurality of user-selectable television channels.

23. In an electronic television programming guide for use in connection with a television receiver, a method for selecting program schedule information for display on said receiver by selecting a plurality of characters in a desired title for one of said programs, the method comprising:

- a) providing a user control means including up/down arrow keys;
- b) displaying a plurality of n character display cells on said television receiver, where n is greater than 1;
- c) displaying an alphanumeric character in the first said display cell in response to a first user control command generated by said user control means;
- d) changing said displayed alphanumeric character in response to depression of one of said up/down arrow keys on said user control means if said displayed alphanumeric character is not the correct first character for said desired title;
- e) selecting said displayed alphanumeric character as said first character of said desired title in response to a second user control command;
- f) displaying a plurality of program titles alphabetically in response to said first selected alphanumeric character;

g) repeating steps c), d), and e) for the second character of said desired title and displaying a plurality of program titles alphabetically in response to said first and second selected alphanumeric characters of said desired title; and

*A2
cancel*

h) repeating steps c), d), and e) for the third character of said desired title and displaying a plurality of program titles alphabetically in response to said first, second and third selected alphanumeric characters of said desired title if said desired title is not displayed following step g). --

REMARKS

Claims 1-23 are now pending in this application, with claims 2-23 added by the above amendment. Claim 1 stands rejected as obvious over U.S. Patent No. 5,353,121 to Young or U.S. Patent No. 5,253,066 to Vogel in view of U.S. Patent No. 5,241,671 to Reed.

Applicants' invention relates to an interactive electronic program guide that permits users to search a database of program schedule information based on the title of the program. Users are provided with a user control means (e.g., a remote control device) that is used to input a plurality of characters in the title of a program. Because remote control devices generally do not include full alphanumeric keyboards, the characters are selected by cycling through letters and numbers until the desired

character is obtained. For example, the channel up/down arrow keys, present on virtually all television, cable decoder box, and VCR remote control devices, may be used to cycle backward and forward through the alphabet and the digits 0-9 in order to select each of the characters.

In a preferred embodiment, the user may select as many as four characters. The system may be configured to search substantially in real time as each of the characters is selected, so that the desired program may be found by selecting less than four characters. As the characters are selected, a number of program titles are displayed beginning with the first alphabetical match for the entered characters. This program title is highlighted in the display to indicate the location of the cursor. As shown in Fig. 38E, in the top portion of the screen the characters are selected by the user and in the lower portion the resulting titles displayed. The user may toggle to the lower portion of the screen to obtain more information about the highlighted program or to manually scroll through the alphabetical listing of displayed titles.

Applicants' invention has particular utility in situations where the user knows of a program he or she wants to watch, but does not know what channel or date and time it is scheduled for broadcast. Using the search by title feature of the claimed invention, a user is able to quickly determine the channel, date and time for the program, a task which otherwise would be time-consuming and frustrating.

Applicants do not dispute that electronic program guides or "EPGs," such as the ones disclosed in the Young and Vogel patents, are known in the art. EPGs have their origin in printed television program guides that typically are sorted by time, i.e., they show the program schedule chronologically for each time slot during the day. More recently, printed guides have been improved to show a grid of television program schedule information for multiple channels and multiple time slots. EPGs have adopted the time and grid formats of printed guides and may also include the ability to search information by channel, category of program, and favorite channel list.

Reed discloses a multimedia database search system for a personal computer or computer terminal where articles can be located by selecting the first letter of the desired subject so that a list of articles having the first letter is provided. The user may scroll through a list of articles or type in the article name using the keyboard (col. 4, lines 28-37; col. 17, lines 9-17). Reed also mentions another encyclopedia system where a user can type in the first few letters of a topic to obtain an alphabetical list of titles (col. 1, lines 45-52).

The Examiner expressly acknowledges that neither Young nor Vogel disclose searching and displaying program titles alphabetically. In addition, there is no teaching or even the slightest suggestion in Young or Vogel to include a search-by-

title capability as described and claimed by applicants. Moreover, there is most certainly no teaching or suggestion to combine Young or Vogel with Reed. If anything, Young and Vogel teach away from a search-by-title feature in an EPG because of the many other ways users can search and access the program listings information, and because of the problems associated with performing character-based searches in an EPG, as discussed below. Nevertheless, the examiner asserts that claim 1 is invalid as obvious over Young or Vogel in view of Reed and states as follows:

[I]t would have been obvious to one of ordinary skill in the art to modify Young's or Vogel's system to include programs alphabetically by title and a selection means for allowing a user to select a title by selecting the first n characters of the title where n is greater than or equal to one, as taught by Reed, for the advantage of providing a flexible user friendly system which facilitates quick retrieval of titles with few keystrokes.

(emphasis added)

Applicants submit that, although Reed discloses searching alphabetically by article title, the Examiner's conclusion that it would have been obvious to one of ordinary skill in the art of EPGs to look to the teachings of Reed is based solely on improper hindsight reconstruction. Applicants do not dispute that the intent of the search-by-title capability in Reed and applicants' invention is to provide a "flexible user friendly system which facilitates quick retrieval of titles with few keystrokes." However, although Reed may accomplish this for a database search system using a

keyboard as the input device, it does not teach or suggest such a system for an EPG.

The requirements and constraints for an EPG system are very different from those for a PC-based database search system. For example, the system disclosed in Reed operates using a full keyboard. As such, it is a simple matter to type in the first few letters of an article title. In contrast, in an EPG environment, the user control device is typically a hand-held remote control transmitter with only a very limited number of keys. Therefore, in terms of performing searching based on alphanumeric characters, EPGs present a problem not present in nor solved by systems such as that described in Reed.

Applicants solve this problem by using existing keys on the remote control device to input the characters of a program title. With applicants' invention, searching based on alphanumeric characters is provided for in a user-friendly manner without cluttering the remote control device with a large number of keys. For example, as disclosed in applicants' specification, the up/down arrow keys used for changing channels in normal television mode may be used to cycle through the letters A-Z and the numbers 0-9 in order to choose the individual letters in a program title.

Therefore, applicants respectfully disagree with the Examiner's conclusion with regard to the obviousness of combining Reed and Young or Vogel because Reed does not teach a system or method for inputting multiple characters of a

title without using a keyboard. Reed thus does not solve the problem of performing character-based searches in an EPG. Although Reed discloses that the first character of a title or topic may be input using a point and click action with a mouse, if an entire title is to be input, Reed discloses that the keyboard is used. In sum, Reed does not solve the problem of providing a system for searching for titles in an EPG where it must be assumed that the user is not provided with a full keyboard.

This argument underscores the fact that EPGs are a unique type of database system with very different requirements and constraints than typical databases accessed using a personal computer. The teachings of other types of database systems with regard to how to access data thus do not necessarily apply to EPGs for this reason. In this case, due t the aforescribed deficiencies in Reed, there would not have been any motivation for one of ordinary skill in the art to look to Reed in order to implement a search-by-title feature in an EPG.

Therefore, applicants submit that the Examiner has used improper hindsight reconstruction to conclude that in view of Reed it would have been obvious to implement title searching in an EPG. In the absence of applicants' disclosure, one of ordinary skill in the art is faced with the dilemma of how to input 36 different characters (A-Z and 0-9) using only a few keys on a remote control device.

Applicants therefore submit that the combination of Reed and Young or Vogel is improper.

Furthermore, even if the teachings of Reed are applied to either Young or Vogel, because Reed does not disclose how to select multiple characters in a title using only a remote control device, one of ordinary skill in the art would still not be possessed of the invention described and claimed by applicants. For example, claim 1 has been amended to recite i) that a plurality of characters in the title are input by the user, and ii) the specific means by which this is done -- providing a user selection means to "cycle forward and backward through a plurality of alphanumeric characters" in order to locate each of the desired characters in the title. Reed does not teach or suggest this specific means for inputting more than the first character of a title because there is no reason to use this type of a system when a full keyboard is available. Applicants therefore submit that the rejection of claim 1 has been traversed.

Dependent claims 2-11 have been added to more fully claim applicants' invention by including some of the additional aspects of the search-by-title feature disclosed in the application, including conducting the search of the listings as each character is chosen so that the user need only input sufficient characters in the title to locate the particular program desired, or changing the display as the different

potential characters are cycled through by the user. These claims are patentable over the art of record for at least the same reasons as claim 1. Independent claims 12-22 are method claims similar to system claims 1-11, respectively, and independent method claim 23 claims the method in a slightly different manner.

In view of the foregoing, applicants respectfully submit that the rejection has been traversed and all claims are in condition for allowance. Prompt consideration and passage to issue are solicited.

Should the Examiner determine that the application is still not in condition for allowance following consideration of this amendment and response, applicants request that the Examiner contact their undersigned attorney at (212) 310-8734 to schedule an interview in order to promptly advance the case to issue.

Respectfully submitted,

Date: March 7, 1996

By: 

Steven J. Rizzi
Reg. No. 37,706
WEIL, GOTSHAL & MANGES LLP
767 Fifth Avenue
New York, New York 10153
(212) 310-8734
Attorneys for Applicants

EXHIBIT

**OFFICE ACTION MAILED JANUARY 30, 1996
IN APPLICATION LEADING TO
U.S. PATENT NO. 5,629,733**



UNITED STATES DEPARTMENT OF COMMERCE
Patent and Trademark Office
 Address: COMMISSIONER OF PATENTS AND TRADEMARKS
 Washington, D.C. 20231

SERIAL NUMBER	FILING DATE	FIRST NAMED INVENTOR	ATTORNEY DOCKET NO.
---------------	-------------	----------------------	---------------------

08/346,603 11/29/94 YOUMAN

R 72118-0003
 EXAMINER

26M1/0130

GRANT, C
 ART UNIT PAPER NUMBER

5

STEVEN J RIZZI
 WEIL GOTSHAL & MANGES
 767 FIFTH AVENUE
 ROOM 3222
 NEW YORK NY 10153

26/02
 DATE MAILED:

01/30/96

This is a communication from the examiner in charge of your application.
 COMMISSIONER OF PATENTS AND TRADEMARKS

☒ This application has been examined ☐ Responsive to communication filed on _____ ☐ This action is made final.

A shortened statutory period for response to this action is set to expire 3 month(s), _____ days from the date of this letter.
 Failure to respond within the period for response will cause the application to become abandoned. 35 U.S.C. 133

Part I THE FOLLOWING ATTACHMENT(S) ARE PART OF THIS ACTION:

- ☒ Notice of References Cited by Examiner, PTO-892.
- ☒ Notice of Draftsman's Patent Drawing Review, PTO-948.
- ☐ Notice of Art Cited by Applicant, PTO-1449.
- ☐ Notice of Informal Patent Application, PTO-152.
- ☐ Information on How to Effect Drawing Changes, PTO-1474.
- ☐ _____

Part II SUMMARY OF ACTION

☒ Claims 1 are pending in the application.

Of the above, claims _____ are withdrawn from consideration.

- ☐ Claims _____ have been cancelled.
- ☐ Claims _____ are allowed.
- ☒ Claims 1 are rejected.
- ☐ Claims _____ are objected to.
- ☐ Claims _____ are subject to restriction or election requirement.
- ☐ This application has been filed with informal drawings under 37 C.F.R. 1.85 which are acceptable for examination purposes.
- ☐ Formal drawings are required in response to this Office action.
- ☐ The corrected or substitute drawings have been received on _____ Under 37 C.F.R. 1.84 these drawings are ☐ acceptable; ☐ not acceptable (see explanation or Notice of Draftsman's Patent Drawing Review, PTO-948).
- ☐ The proposed additional or substitute sheet(s) of drawings, filed on _____, has (have) been ☐ approved by the examiner; ☐ disapproved by the examiner (see explanation).
- ☐ The proposed drawing correction, filed _____, has been ☐ approved; ☐ disapproved (see explanation).
- ☐ Acknowledgement is made of the claim for priority under 35 U.S.C. 119. The certified copy has ☐ been received ☐ not been received ☐ been filed in parent application, serial no. _____; filed on _____.
- ☐ Since this application appears to be in condition for allowance except for formal matters, prosecution as to the merits is closed in accordance with the practice under Ex parte Quayle, 1935 C.D. 11; 453 O.G. 213.
- ☐ Other

EXAMINER'S ACTION

Art Unit: 2602

1. The following is a quotation of 35 U.S.C. § 103 which forms the basis for all obviousness rejections set forth in this Office action:

A patent may not be obtained though the invention is not identically disclosed or described as set forth in section 102 of this title, if the differences between the subject matter sought to be patented and the prior art are such that the subject matter as a whole would have been obvious at the time the invention was made to a person having ordinary skill in the art to which said subject matter pertains. Patentability shall not be negated by the manner in which the invention was made.

Subject matter developed by another person, which qualifies as prior art only under subsection (f) or (g) of section 102 of this title, shall not preclude patentability under this section where the subject matter and the claimed invention were, at the time the invention was made, owned by the same person or subject to an obligation of assignment to the same person.

2. Claim 1 is rejected under 35 U.S.C. § 103 as being unpatentable over (Young or Vogel) and Reed.

Considering claim 1, Young discloses an electronic television programming guide for use in connection with a television receiver for displaying television programs. Young's system comprises: 1) a user control (remote control) of figure 21 for issuing control commands; 2) a data processing means (cable decoder 202, VBI decoder 222, CPU 228) of figure 22A for processing the control commands; and 3) a video display generator (224) of figure 22A adapted to receive control commands for generating and displaying television program titles.

Although Young discloses a selection means (keys 156 of figure 21), he fails to specifically disclose displaying the

Art Unit: 2602

programs alphabetically by title and a selection means for allowing a user to select a title by selecting the first n characters of the title where n is greater than or equal to one as recited in the claim.

Vogel discloses an electronic television programming guide system comprising a user control (remote control 112), a data processing means (receiver 102, demodulator 103, microprocessor 104) and video display generator (109).

Although Vogel discloses a selection means (the four triangular and sel keys of figure 2), he fails to specifically disclose displaying the programs alphabetically by title and a selection means for allowing a user to select a title by selecting the first n characters of the title where n is greater than or equal to one as recited in the claim.

Reed discloses a multimedia search system comprising an alphabetical listing of article (book, picture etc.) titles. The user is allowed to select a title by entering one or more characters of the selected title and a listing of the article titles that are closest to the selected title are displayed. See col. 1, lines 45-52, col. 4, lines 28-37 and col. 17, lines 9-17.

Therefore, it would have been obvious to one of ordinary skill in the art to modify Young's or Vogel's system to include programs alphabetically by title and a selection means for allowing a user to select a title by selecting the first n

Serial Number: 08/346,603

-4-

Art Unit: 2602

characters of the title where n is greater than or equal to one, as taught by Reed, for the advantage of providing a flexible user friendly system which facilitates quick retrieval of titles with few keystrokes.

3. The lengthy specification has not been checked to the extent necessary to determine the presence of all possible minor errors. Applicant's cooperation is requested in correcting any errors of which applicant may become aware in the specification.

4. The prior art made of record and not relied upon is considered pertinent to applicant's disclosure.

Sakuma et al. disclose program schedule system.

5. Any inquiry concerning this communication or earlier communications from the examiner should be directed to Chris Grant whose telephone number is (703) 305-4755. The examiner can normally be reached on Monday-Friday from 8:00am to 9:00pm.

If attempts to reach the examiner by telephone are unsuccessful, the examiner's supervisor, James Groody, can be reached on (703) 305-4702. The fax phone number for this Group is (703) 305-9509.

Any inquiry of a general nature or relating to the status of this application or proceeding should be directed to the Group receptionist whose telephone number is (703) 305-4700.

ck

Chris Grant

January 22, 1995


SAFET METJAHIC
PRIMARY EXAMINER
GROUP 2600

FORM PTO-852 (REV. 2-85)		U.S. DEPARTMENT OF COMMERCE PATENT AND TRADEMARK OFFICE		SERIAL NO. 08/346603	GROUP ART UNIT 2602	ATTACHMENT TO PAPER NUMBER 5
NOTICE OF REFERENCES CITED				APPLICANT(S) YOUNMAN		

U.S. PATENT DOCUMENTS							
*	DOCUMENT NO.	DATE	NAME	CLASS	SUB-CLASS	FILING DATE IF APPROPRIATE	
A	5353121	10/4/94	Young	348	563		
B	5253066	10/12/93	Vogel	348	906		
C	5416508	5/16/95	Sakuma et al	348	3		
D	5241671	8/31/93	Reed et al.	395	600		
E							
F							
G							
H							
I							
J							
K							

FOREIGN PATENT DOCUMENTS							
*	DOCUMENT NO.	DATE	COUNTRY	NAME	CLASS	SUB-CLASS	PERTINENT SHTS. OWD PP. SPEC.
L							
M							
N							
O							
P							
Q							

OTHER REFERENCES (Including Author, Title, Date, Pertinent Pages, Etc.)	
R	
S	
T	
U	

EXAMINER Chris Grant	DATE 1/22/96	
--------------------------------	------------------------	--

* A copy of this reference is not being furnished with this office action.
(See Manual of Patent Examining Procedure, section 707.05 (a).)